

## INDUSTRIAL COMPONENT DATA

# T3-8-SOND\*/Z 907920 Y7-907920 EATON ELECTRIC

## Non-standard switch, T3, 32 A, rear mounting, 8 contact unit(s)

Brand: EATON - MOELLER | Manufacturer Part Number: T3-8-SOND\*/Z



|                 |                     |
|-----------------|---------------------|
| Manufacturer    | EATON - MOELLER     |
| MPN / Reference | T3-8-SOND*/Z        |
| Catalog number  | Y7-907920           |
| Category        | Switch disconnecter |
| Minimum order   | 10 Pcs              |
| Document ID     | EO-A460A1D3C0       |
| Generated       | 2026-08-04          |

### Product Overview

Non-standard switch, T3, 32 A, rear mounting, 8 contact unit(s)

T3-8-SOND\*/Z

Eaton Moeller® series T3 Non-standard switch, T3, 32 A, rear mounting, 8 contact unit(s)

Non-standard switch, Product range: Non-standard switch, Part group reference: T3, Notes: customized version according to form, Degree of Protection: Front IP65, Design: rear mounting, Motor rating AC-23A, 50 - 60 Hz 400 V: P = 15 kW, Rated uninterrupted current: I<sub>u</sub> = 32 A, 8 contact unit(s), Standards: IEC/EN 60947, VDE 0660, IEC/EN 60204, Switch-disconnector according to IEC/EN 60947-3

## STRUCTURED PRODUCT DATA

### Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

### Classification & Catalog Path

Catalog path EATON - MOELLER > Disconnectors and Cam Switches

### Additional Product Information

General specifications

Product Name Eaton Moeller® series T3 Non-standard switch Catalog Number 907920 Model Code T3-8-SOND\*/Z Product Length/Depth 202 mm Product Height 54 mm Product Width 61 mm Product Weight 0.446 kg Certifications VDE 0660

IEC/EN 60947-3

IEC/EN 60947

IEC/EN 60204

ETIM for 907920 Low-voltage industrial controls and switchgear (EC000216)

|                                                                    |  |
|--------------------------------------------------------------------|--|
| Feature Name                                                       |  |
| Feature Value                                                      |  |
| Version as main switch (EF006981)                                  |  |
| No                                                                 |  |
| Version as maintenance-/service switch (EF006986)                  |  |
| No                                                                 |  |
| Version as safety switch (EF006985)                                |  |
| No                                                                 |  |
| Version as emergency stop installation (EF006959)                  |  |
| No                                                                 |  |
| Version as reversing switch (EF009408)                             |  |
| No                                                                 |  |
| Number of switches (EF005586)                                      |  |
| 1                                                                  |  |
| Rated operating voltage (EF001435)                                 |  |
| 690 V                                                              |  |
| Rated permanent current I <sub>u</sub> (EF001389)                  |  |
| 32 A                                                               |  |
| Rated permanent current at AC-23, 400 V (EF011777)                 |  |
| 32 A                                                               |  |
| Rated permanent current at AC-21, 400 V (EF009165)                 |  |
| 32 A                                                               |  |
| Rated operation power at AC-3, 400 V (EF001364)                    |  |
| 11 kW                                                              |  |
| Rated short-time withstand current I <sub>cw</sub> (EF007050)      |  |
| 0.65 kA                                                            |  |
| Rated operation power at AC-23, 400 V (EF007027)                   |  |
| 15 kW                                                              |  |
| Switching power at 400 V (EF009166)                                |  |
| 15 kW                                                              |  |
| Conditioned rated short-circuit current I <sub>q</sub> (EF001444)  |  |
| 1 kA                                                               |  |
| Number of auxiliary contacts as normally closed contact (EF001377) |  |
| 0                                                                  |  |
| Number of auxiliary contacts as normally open contact (EF001376)   |  |
| 0                                                                  |  |
| Number of auxiliary contacts as change-over contact (EF003531)     |  |
| 0                                                                  |  |
| Motor drive optional (EF007386)                                    |  |
| No                                                                 |  |
| Motor drive integrated (EF006697)                                  |  |
| No                                                                 |  |
| Voltage release optional (EF007491)                                |  |
| No                                                                 |  |
| Device construction (EF008240)                                     |  |
| Built-in device fixed built-in technique                           |  |
| Suitable....                                                       |  |

## REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / T3-8-SOND\*/Z with the required quantity to [info@electricaonline.com](mailto:info@electricaonline.com) or use [electricaonline.com/request-quote](https://electricaonline.com/request-quote).

### GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.