

INDUSTRIAL COMPONENT DATA

5093572 OBO BETTERMANN ARRESTER 1+2 V50-1-385

Brand: OBO BETTERMANN | Manufacturer Part Number: V50-1-385



Manufacturer	OBO BETTERMANN
MPN / Reference	V50-1-385
Catalog number	5093572
Category	Combined arrester for power supply systems
Minimum order	1 Pcs
Document ID	EO-B3D963B77D
Generated	2026-08-02

Product Overview

ARRESTER 1+2 V50-1-385

Combination arrester V50, 1-pole 385 V. Lightning current combination arrester, type 1+2• For lightning current equipotential bonding to VDE 0185-305 (IEC 62305)• Lightning current arresting capacity of 12.5 kA (10/350) per pole and up to 50 kA (10/350) in total• Modular, plug-in arrester with cut-off unit and visual status display • Locking mechanism with vibration protection and voltage keying • Plastic to UL 94 V-0• The remote signalling (FS) variants have a potential-free changeover contact for remote signalling Application: Lightning current equipotential bonding for buildings of class III and IV.* Complete = Plug-in arrester and base

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path OBO BETTERMANN > TBS Transient and lightning protection systems - OBO BETTERMANN

Additional Product Information

Approvals VDE, KEMA, UL, ÖVE

Blow-out no

CO2 Footprint (GWP) Cradle-to-Gate 0,6217 kg CO2e / 1 Piece

Conductor cross-section, flexible (fine-wire), max. 2 AWG

Conductor cross-section, flexible (fine-wire), max. 35 mm²

Conductor cross-section, flexible (fine-wire), min. 16 AWG

Conductor cross-section, flexible (fine-wire), min. 1,5 mm²

Conductor cross-section, rigid (single-wire/multiwire), max. 2 AWG

Conductor cross-section, rigid (single-wire/multiwire), max. 35 mm²

Conductor cross-section, rigid (single-wire/multiwire), min. 1,5 mm²

Conductor cross-section, rigid (single-wire/multiwire), min. 16 AWG

Connection cross-section, FM terminals, max. 16 AWG

Connection cross-section, FM terminals, max. 1,5 mm²

Connection cross-section, FM terminals, min. 21 AWG

Connection cross-section, FM terminals, min. 0,5 mm²

Dimension 385V

Housing material surge protection components PA UL 94 V-0

Installation type DIN rail 35 mm

Integrated back-up fuse no

Lightning surge current (10/350 us) 12,5 kA

Material Polyamide

Max. mains-side overcurrent protection 160 A gL/gG

Maximum back-up fuse 160 A

Maximum continuous voltage (L-N) 385 V

Maximum continuous voltage AC 385 V

Maximum discharge current (8/20 us) 50 kA

Maximum discharge current (8/20 us) [L-N] 50 kA

Minimum distance 1,5 mm

Network form TN

Nominal discharge current (8/20 μs) 30 kA

Nominal discharge current (8/20 μs) [L-N] 30 kA

Nominal voltage AC (50/60 Hz) 350 V

Operating temperature, max. 80 °C

Operating temperature, min. -40 °C

Permit...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send OBO BETTERMANN / V50-1-385 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.