

INDUSTRIAL COMPONENT DATA

5093590 OBO BETTERMANN ARRESTER 1+2 V50-1+NPE+FS-385

Brand: OBO BETTERMANN | Manufacturer Part Number: V50-1+NPE+FS-385



Manufacturer	OBO BETTERMANN
MPN / Reference	V50-1+NPE+FS-385
Catalog number	5093590
Category	Combined arrester for power supply systems
Minimum order	1 Pcs
Document ID	EO-D0170241A4
Generated	2026-08-03

Product Overview

ARRESTER 1+2 V50-1+NPE+FS-385

Combination arrester V50, 1-pole + NPE with FS 385 V. Lightning current combination arrester, type 1+2• For lightning current equipotential bonding to VDE 0185-305 (IEC 62305)• Lightning current arresting capacity of 12.5 kA (10/350) per pole and up to 50 kA (10/350) in total• Modular, plug-in arrester with cut-off unit and visual status display • Locking mechanism with vibration protection and voltage keying • Plastic to UL 94 V-0• The remote signalling (FS) variants have a potential-free changeover contact for remote signalling Application: Lightning current equipotential bonding for buildings of class III and IV.* Complete = Plug-in arrester and base

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path OBO BETTERMANN > TBS Transient and lightning protection systems - OBO BETTERMANN

Additional Product Information

Approvals VDE, KEMA, UL, ÖVE

Arrester surge current (8/20 µs) [total] 80 kA

Blow-out no

CO2 Footprint (GWP) Cradle-to-Gate 1,4814 kg CO2e / 1 Piece

Combined voltage protection level [L-PE] 2,5 kV

Conductor cross-section, flexible (fine-wire), max. 2 AWG

Conductor cross-section, flexible (fine-wire), max. 35 mm²

Conductor cross-section, flexible (fine-wire), min. 1,5 mm²

Conductor cross-section, flexible (fine-wire), min. 16 AWG

Conductor cross-section, rigid (single-wire/multiwire), max. 35 mm²
Conductor cross-section, rigid (single-wire/multiwire), max. 2 AWG
Conductor cross-section, rigid (single-wire/multiwire), min. 1,5 mm²
Conductor cross-section, rigid (single-wire/multiwire), min. 16 AWG
Connection cross-section, FM terminals, max. 16 AWG
Connection cross-section, FM terminals, max. 1,5 mm²
Connection cross-section, FM terminals, min. 21 AWG
Connection cross-section, FM terminals, min. 0,5 mm²
Dimension 385V
FM contacts Changeover
Follow current quenching capacity (eff) [N-PE] 0,1 kA
Housing material surge protection components PA UL 94 V-0
Installation type DIN rail 35 mm
Integrated back-up fuse no
Lightning surge current (10/350 us) 12,5 kA
Lightning surge current (10/350) 25 kA
Material Polyamide
Max. mains-side overcurrent protection 160 A gL/gG
Maximum back-up fuse 160 A
Maximum continuous voltage (L-N) 385 V
Maximum continuous voltage (N-PE) 255 V
Maximum continuous voltage AC 385 V
Maximum discharge current (8/20 us) 50 kA
Maximum discharge current (8/20 us) [L...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send OBO BETTERMANN / V50-1+NPE+FS-385 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten PI #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.