

INDUSTRIAL COMPONENT DATA

MINI MCR-2-I-I 2901998 PHOENIX CONTACT Signal conditioner

Brand: PHOENIX CONTACT | Manufacturer Part Number: MINI MCR-2-I-I



Manufacturer	PHOENIX CONTACT
MPN / Reference	MINI MCR-2-I-I
Catalog number	2901998
Category	Isolation amplifier
Minimum order	1 Pcs
Document ID	EO-F7549C52DA
Generated	2026-09-21

Product Overview

Signal conditioner

3-way separation amplifier with plug-in connection technology for galvanic separation of analogue signals. Input Signal: 0(4) mA ... 20 mA, output signal: 0(4) mA ... 20 mA, screw connection technology

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > INTERFACE Components (IF)

Additional Product Information

Key Commercial Data

Orderkey 2901998

Packing unit 1 pc

Catalog page Page 74 (C-5-2017)

GTIN 4046356649490

Weight per Piece (excluding packing) 94.700 g

Custom tariff number 85437090

Country of origin DE (Germany)

Note

Utilization restriction EMC: class A product, see manufacturer's declaration in the download area

Dimensions

Width 6.2 mm

Height 110.5 mm

Depth 120.5 mm

Ambient conditions

Ambient temperature (operation) -40 °C ... 70 °C

Ambient temperature (storage/transport) -40 °C ... 85 °C

Permissible humidity (operation) 5 % ... 95 % (non-condensing)

Input data

Number of inputs 1

Configurable/programmable no

Current input signal 0 mA ... 20 mA

4 mA ... 20 mA

Input resistance current input approx. 63 Ω (+ 0.7 V for test diode)

Output data

Number of outputs 1

Configurable/programmable no

Current output signal 0 mA ... 20 mA

4 mA ... 20 mA

Max. output current 22 mA

Load/output load current output ≤ 600 Ω (at 20 mA)

Ripple < 20 mVPP(at 600 Ω)

Transmission Behavior 1:1 to input signal

Power supply

Nominal supply voltage 24 V DC

Supply voltage range 9.6 V DC ... 30 V DC (The DIN rail bus connector (ME 6,2 TBUS-2 1,5/5-ST-3,81 GN, Order No. 2869728) can be used to bridge the supply voltage. It can be snapped onto a 35 mm DIN rail according to EN 60715))

Typical current consumption 25 mA (24 V DC)

54 mA (12 V DC)

Power consumption ≤ 800 mW (at 9.6 V DC)

Connection data

Connection method Screw connection

Single conductor/terminal point, solid, with ferrule, min. 0.2 mm²

Single cond...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / MINI MCR-2-I-I with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.