

INDUSTRIAL COMPONENT DATA

CSS 0.37-1/3 1201135 PHOENIX CONTACT Speed starter with soft start and adjustable speed for starting and rev..

Brand: PHOENIX CONTACT | Manufacturer Part Number: CSS 0.37-1/3



Manufacturer	PHOENIX CONTACT
MPN / Reference	CSS 0.37-1/3
Catalog number	1201135
Category	Speed controller
Minimum order	1 Pcs
Document ID	EO-68F9217603
Generated	2026-09-21

Product Overview

Speed starter with soft start and adjustable speed for starting and reversing motors up to 230 V AC and 0.37 kW, adjustable motor protection, analog input, STO function up to SIL 3 / PL e, single-phase load input

Speed starter with soft start and configurable speed for starting and reversing motors up to 480 V AC and 0.37 kW, configurable motor protection, STO function up to SIL 3 / PL e, Push-in connection, single-phase load input

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > INTERFACE Components (IF)

Additional Product Information

Technical dataProduct propertiesProduct type Speed starter

Product family CONTACTRON

Operating elements Push button

Rotary switch

Insulation characteristics

Pollution degree 2

Electrical propertiesNumber of phases 1

Input dataMains

Number of phases 1

Input voltage 230 V AC

240 V AC

Input voltage range 110 V AC ... 240 V AC -15 % ... +10 %

Frequency range 47 Hz ... 63 Hz
Nominal current 5.3 A (no line reactor)
4.8 A (with line reactor)
Output dataNominal motor power 0.37 kW
Apparent power 1 kVA
Nominal output current (IN) 2.5 A (4 kHz)
2.1 A (8 kHz)
1.4 A (16 kHz)
Output frequency 0 Hz ... 500 Hz
Power dissipation 22 W (2 kHz)
26 W (4 kHz)
24 W (8 kHz)
23 W (16 kHz)
9 W (stand by)
Output current ≤ 3.75 A (180 s)
 ≤ 1.875 A (180 s, during recovery time)
 ≤ 4.5 A (15 s)
 ≤ 1.25 A (15 s, during recovery time)
Recovery time 150 s (180 s)
12 s (15 s)
Overload time 30 s (180 s)
3 s (15 s)
Discharge time 3 min. (Intermediate circuit capacitors)
Switching
Output name Relay output
Contact switching type 1 changeover contact
Maximum switching voltage 125 V AC
30 V DC
Maximum inrush current 3 A
Inrush current, minimum 10 mA (5 V DC)
Connection dataCross section AWG (converted acc. to IEC)
Power-level terminals
Connection method Push-in connection
Stripping length 10 mm
Conductor cross section rigid 0.2 mm² ... 6 mm²
Conductor cross section flexible 0.2 mm² ... 6 mm²
0.2 mm² ... 4 mm² (with ferrule)
Conductor cross section AWG 24 ... 10
Control terminals
Connection method Push-in connection...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / CSS 0.37-1/3 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.