

## INDUSTRIAL COMPONENT DATA

# FRONT 2,5-V/SA 5 BU 1701544 PHOENIX CONTACT PCB terminal block

Brand: PHOENIX CONTACT | Manufacturer Part Number: FRONT 2,5-V/SA 5 BU



|                 |                                |
|-----------------|--------------------------------|
| Manufacturer    | PHOENIX CONTACT                |
| MPN / Reference | FRONT 2,5-V/SA 5 BU            |
| Catalog number  | 1701544                        |
| Category        | Printed circuit board terminal |
| Minimum order   | 50 Pcs                         |
| Document ID     | EO-FF31031B2E                  |
| Generated       | 2026-09-29                     |

## Product Overview

PCB terminal block

Terminal block for printed circuit board, nominal current: 24 A, nominal voltage (III/2): 400 V, nominal cross-section: 2.5 mm<sup>2</sup>, number of potentials: 1, number of rows: 1, number of poles per row: 1, article family: FRONT 2.5-V/SA 5, pitch: 5 mm, connection type: Front screw connection, mounting: Wave soldering, Conductor/PCB connection direction: 90 °, color: blue, Pin arrangement: Linear pin arrangement, Pin length [P]: 3.5 mm, number of solder pins per potential: 2, packaging type: boxed packaging. The item can be aligned with different numbers of poles!

## STRUCTURED PRODUCT DATA

## Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

## Classification & Catalog Path

|              |                                        |
|--------------|----------------------------------------|
| Catalog path | PHOENIX CONTACT > PCB Connectors (PCC) |
|--------------|----------------------------------------|

## Additional Product Information

Key Commercial Data

Orderkey 1701544

Packing unit 50 pc

Minimum order quantity 50 pc

Note Made to Order (non-returnable)

GTIN 4017918315269

Weight per Piece (excluding packing) 3.370 g

Custom tariff number 85369010

Country of origin DE (Germany)

Item properties

Brief article description PCB terminal block

Range of articles FRONT 2,5-V/SA 5

Pitch 5 mm

Number of positions 1

Connection method Front screw connection

Screw thread M2,5

Mounting type Wave soldering

Pin layout Linear double pinning

Number of levels 1

Electrical parameters

Rated current 24 A

Rated insulation voltage (III/2) 400 V

Rated surge voltage (III/2) 4 kV

Connection capacity

Conductor cross section solid 0.2 mm<sup>2</sup> ... 2.5 mm<sup>2</sup>

Conductor cross section flexible 0.2 mm<sup>2</sup> ... 2.5 mm<sup>2</sup>

Conductor cross section AWG / kcmil 24 ... 14

Conductor cross section flexible, with ferrule without plastic sleeve 0.25 mm<sup>2</sup> ... 1.5 mm<sup>2</sup>

Conductor cross section, flexible, with ferrule, with plastic sleeve 0.25 mm<sup>2</sup> ... 1.5 mm<sup>2</sup>

2 conductors with same cross section, solid 0.2 mm<sup>2</sup> ... 0.75 mm<sup>2</sup>

2 conductors with same cross section, flexible 0.2 mm<sup>2</sup> ... 0.75 mm<sup>2</sup>

2 conductors with same cross section, stranded, ferrules without plastic sleeve 0.25 mm<sup>2</sup> ... 0.34 mm<sup>2</sup>

Stripping length 9 mm

Torque 0.4 Nm ... 0.5 Nm

Material data - contact

Note WEEE/RoHS-compliant, free of whiskers according to IEC 60068-2-82/JEDEC JESD 201

Contact material Cu alloy

Surface characteristics hot-dip tin-plated

Metal surface terminal point (top layer) Tin (4 - 8 µm Sn)

M...

## REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / FRONT 2,5-V/SA 5 BU with the required quantity to [info@electricaonline.com](mailto:info@electricaonline.com) or use [electricaonline.com/request-quote](https://electricaonline.com/request-quote).

### GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.