INDUSTRIAL COMPONENT DATA

PLC-RSC- 12DC/21/MS 2909648 PHOENIX CONTACT Relay Module

Brand: PHOENIX CONTACT | Manufacturer Part Number: PLC-RSC-12DC/21/MS



Manufacturer	PHOENIX CONTACT
MPN / Reference	PLC-RSC-12DC/21/MS
Catalog number	2909648
Category	Switching relay
Minimum order	1 Pcs
Document ID	EO-1384DBA7F1
Generated	2026-11-18

Product Overview

Relay Module
PLC-INTERFACE, consisting of PLC-BSC.../21 base terminal block with screw connection and plug-in miniature relay with power contact and manual operation, 1 switched contact, input voltage 12 V DC

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	PHOENIX CONTACT > Industrial Relays

Additional Product Information

Key Commercial Data
Orderkey 2909648
Packing unit 10 pc
Note Made to Order (non-returnable)
Catalog page Page 373 (C-5-2017)
GTIN 4055626377834
Weight per Piece (excluding packing) 31.060 g
Custom tariff number 85364190
Country of origin DE (Germany)
Note
Utilization restriction EMC: class A product, see manufacturer's declaration in the download area
Note Separating plate PLC-ATP must be installed for voltages larger than 250 V (L1, L2, L3) between identical terminal blocks in adjacent modules. Potential bridging is then carried out with FBST 8-PLC... or FBST 500....

Dimensions
Width 6.2 mm
Height 80 mm
Depth 94 mm
Ambient conditions
Ambient temperature (operation) -40 °C ... 60 °C
Ambient temperature (storage/transport) -40 °C ... 85 °C
Coil side
Nominal input voltage UN 12 V DC
Typical input current at UN 15.3 mA
Typical response time 5 ms
Typical release time 8 ms
Protective circuit Reverse polarity protection Polarity protection diode
Free-wheeling diode Damping diode
Operating voltage display Yellow LED
Power dissipation for nominal condition 0.18 W
Contact side
Contact type 1 PDT
Type of switch contact Single contact
Contact material AgSnO
Maximum switching voltage 250 V AC/DC (The separating plate PLC-ATP should be installed for voltages larger than 250 V (L1, L2, L3) between identical terminal blocks in adjacent modules. Potential bridging is then carried out with FBST 8-PLC... or ...FBST 500...)
Minimum switching voltage 5 V (at 100 mA)
Min. switching current 10 mA...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / PLC-RSC-12DC/21/MS with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.