

**INDUSTRIAL COMPONENT DATA**

# CSS 0.37-1/3 1201135 PHOENIX CONTACT Speed starter with soft start and adjustable speed for starting and rev..

Brand: PHOENIX CONTACT | Manufacturer Part Number: CSS 0.37-1/3



|                 |                  |
|-----------------|------------------|
| Manufacturer    | PHOENIX CONTACT  |
| MPN / Reference | CSS 0.37-1/3     |
| Catalog number  | 1201135          |
| Category        | Speed controller |
| Minimum order   | 1 Pcs            |
| Document ID     | EO-FC85685A48    |
| Generated       | 2026-08-04       |

## Product Overview

Speed starter with soft start and adjustable speed for starting and reversing motors up to 230 V AC and 0.37 kW, adjustable motor protection, analog input, STO function up to SIL 3 / PL e, single-phase load input

Speed starter with soft start and configurable speed for starting and reversing motors up to 480 V AC and 0.37 kW, configurable motor protection, STO function up to SIL 3 / PL e, Push-in connection, single-phase load input

**STRUCTURED PRODUCT DATA**

## Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

## Classification & Catalog Path

Catalog path      PHOENIX CONTACT &gt; INTERFACE Components (IF)

## Additional Product Information

Technical dataProduct propertiesProduct type Speed starter

Product family CONTACTRON

Operating elements Push button

Rotary switch

Insulation characteristics

Pollution degree 2

Electrical propertiesNumber of phases 1

Input dataMains

Number of phases 1

Input voltage 230 V AC

240 V AC

Input voltage range 110 V AC ... 240 V AC -15 % ... +10 %

Frequency range 47 Hz ... 63 Hz  
Nominal current 5.3 A (no line reactor)  
4.8 A (with line reactor)  
Output dataNominal motor power 0.37 kW  
Apparent power 1 kVA  
Nominal output current (IN) 2.5 A (4 kHz)  
2.1 A (8 kHz)  
1.4 A (16 kHz)  
Output frequency 0 Hz ... 500 Hz  
Power dissipation 22 W (2 kHz)  
26 W (4 kHz)  
24 W (8 kHz)  
23 W (16 kHz)  
9 W (stand by)  
Output current  $\leq 3.75$  A (180 s)  
 $\leq 1.875$  A (180 s, during recovery time)  
 $\leq 4.5$  A (15 s)  
 $\leq 1.25$  A (15 s, during recovery time)  
Recovery time 150 s (180 s)  
12 s (15 s)  
Overload time 30 s (180 s)  
3 s (15 s)  
Discharge time 3 min. (Intermediate circuit capacitors)  
Switching  
Output name Relay output  
Contact switching type 1 changeover contact  
Maximum switching voltage 125 V AC  
30 V DC  
Maximum inrush current 3 A  
Inrush current, minimum 10 mA (5 V DC)  
Connection dataCross section AWG (converted acc. to IEC)  
Power-level terminals  
Connection method Push-in connection  
Stripping length 10 mm  
Conductor cross section rigid 0.2 mm<sup>2</sup> ... 6 mm<sup>2</sup>  
Conductor cross section flexible 0.2 mm<sup>2</sup> ... 6 mm<sup>2</sup>  
0.2 mm<sup>2</sup> ... 4 mm<sup>2</sup> (with ferrule)  
Conductor cross section AWG 24 ... 10  
Control terminals  
Connection method Push-in connection...

## REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / CSS 0.37-1/3 with the required quantity to [info@electricaonline.com](mailto:info@electricaonline.com) or use [electricaonline.com/request-quote](https://electricaonline.com/request-quote).

### GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.