

INDUSTRIAL COMPONENT DATA

ELR H3-IES-PT/500AC-9-IOL 2908672 PHOENIX CONTACT

Hybrid motor starter

Brand: PHOENIX CONTACT | Manufacturer Part Number: ELR H3-IES-PT/500AC-9-IOL



Manufacturer	PHOENIX CONTACT
MPN / Reference	ELR H3-IES-PT/500AC-9-IOL
Catalog number	2908672
Category	Motor starter/Motor starter combination
Minimum order	1 Pcs
Document ID	EO-C7D1839B62
Generated	2026-08-06

Product Overview

Hybrid motor starter

Networkable hybrid start controller for starting 3~ AC motors up to 500 V AC and 9 A output current, with adjustable overload disconnection, emergency stop function up to SIL 3/PL e and push-in connection. Connection to IO-Link.

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > INTERFACE Components (IF)

Additional Product Information

Key Commercial Data

Orderkey 2908672

Packing unit 1 pc

Note Made to Order (non-returnable)

Catalog page Page 27 (C-5-2017)

GTIN 4055626321271

Weight per Piece (excluding packing) 282.700 g

Custom tariff number 85371098

Country of origin DE (Germany)

Note

Type of note Notes on operation

Note If this device is to be used in combination with the CrossPowerSystem power distribution board, the device mount for the 16 A fuse (order designation: EM-CPS-DA-22,5F/16A; order number: 1002668) is required in order to attach the hybrid

motor starter to the power distribution board.

Dimensions

Width 22.5 mm

Height 126.8 mm

Depth 113.7 mm

Ambient conditions

Ambient temperature (operation) -5 °C ... 55 °C (observe derating)

Ambient temperature (storage/transport) -40 °C ... 80 °C

Degree of protection IP20

Device supply

Rated control circuit supply voltage US 24 V DC

Control supply voltage range 19.2 V DC ... 30 V DC

Rated control supply current IS 65 mA

Type of protection Surge protection

Reverse polarity protection

Input data

Input name Enable input

Rated actuating voltage UC 24 V DC

Triggering voltage range 19.2 V DC ... 30 V DC

Rated actuating current IC 7 mA

Switching threshold 9.6 V ("0" signal)

19.2 V ("1" signal)

Switching level < 5 V DC (For EMERGENCY STOP)

Typical turn-off time < 30 ms

Output data load output

Output name AC output

Rated operating voltage Ue 500 V AC

Operating voltage range 42 V AC ... 550 V AC

Rated operating current Ie 9 A (AC-51)

7 A (AC-53a)

Mains frequency 50/60...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / ELR H3-IES-PT/500AC-9-IOL with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.