


## INDUSTRIAL COMPONENT DATA

# FK-MCP 1,5/ 6-STF-3,5 BD:1-6 1701985 PHOENIX CONTACT Plug

Brand: PHOENIX CONTACT | Manufacturer Part Number: FK-MCP 1,5/ 6-STF-3,5 BD:1-6



|                 |                              |
|-----------------|------------------------------|
| Manufacturer    | PHOENIX CONTACT              |
| MPN / Reference | FK-MCP 1,5/ 6-STF-3,5 BD:1-6 |
| Catalog number  | 1701985                      |
| Category        | Cable connector              |
| Minimum order   | 50 Pcs                       |
| Document ID     | EO-7F1E8648C7                |
| Generated       | 2026-08-05                   |

## Product Overview

### Plug

Connector for printed circuit board, nominal section: 1.5 mm<sup>2</sup>, color: green, nominal current: 8 A, nominal voltage (III/2): 160 V, contact surface: Tin, contact type: Female, number of potentials: 6, number of rows: 1, number of poles: 6, number of connections: 6, family of articles: FK-MCP 1.5/.. -STF, pitch: 3.5mm, connection type: Push-in spring connection, conductor/printed circuit board connection direction: 0°, plug-in system: COMBICON MC 1.5, lock: Screw lock, fixing type: Air clamping (screw), packaging type: boxed

## STRUCTURED PRODUCT DATA

## Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

## Classification & Catalog Path

|              |                                        |
|--------------|----------------------------------------|
| Catalog path | PHOENIX CONTACT > PCB Connectors (PCC) |
|--------------|----------------------------------------|

## Additional Product Information

### Key Commercial Data

Orderkey 1701985

Packing unit 1

GTIN 4046356569019

Custom tariff number 85366990

### Dimensions

Length [ l ] 20.8 mm

Width [ w ] 31.3 mm

Height [ h ] 12.4 mm

Pitch 3.5 mm

Dimension a 17.5 mm

General

Range of articles FK-MCP 1,5/...-STF

Number of positions 6

Connection method Push-in spring connection

Rated voltage (III/3) 160 V

Connection in acc. with standard EN-VDE

Nominal current I<sub>N</sub> 8 A

Nominal cross section 1.5 mm<sup>2</sup>

Connection data

Conductor cross section solid min. 0.14 mm<sup>2</sup>

Conductor cross section solid max. 1.5 mm<sup>2</sup>

Conductor cross section flexible min. 0.14 mm<sup>2</sup>

Conductor cross section flexible max. 1.5 mm<sup>2</sup>

Conductor cross section flexible, with ferrule without plastic sleeve min. 0.25 mm<sup>2</sup>

Conductor cross section flexible, with ferrule without plastic sleeve max. 1.5 mm<sup>2</sup>

Conductor cross section flexible, with ferrule with plastic sleeve min. 0.25 mm<sup>2</sup>

Conductor cross section flexible, with ferrule with plastic sleeve max. 0.5 mm<sup>2</sup>

Conductor cross section AWG min. 26

Conductor cross section AWG max. 16

Specifications for ferrules

Recommended crimping pliers 1212034 CRIMPFOX 6

Ferrules without insulating collar, according to DIN 46228-1 Cross section: 0.25 mm<sup>2</sup>; Length: 7 mm ... 9 mm

Cross section: 0.34 mm<sup>2</sup>; Length: 7 mm ... 9 mm

Cross section: 0.5 mm<sup>2</sup>; Length: 8 mm ... 9 mm

Cross section: 0.75 mm<sup>2</sup>; Length: 8 mm ... 9 mm

Cross section: 1 mm<sup>2</sup>; Length: 8 mm ... 9 mm

Cross section: 1.5 mm<sup>2</sup>; Length: 8 mm ... 9 mm

Standards and Regulations

Connection in acc. with st...

## REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / FK-MCP 1,5/ 6-STF-3,5 BD:1-6 with the required quantity to [info@electricaonline.com](mailto:info@electricaonline.com) or use [electricaonline.com/request-quote](https://electricaonline.com/request-quote).

### GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.