

INDUSTRIAL COMPONENT DATA

FRONT-MC 1,5/ 8-STF-3,81BUBD1Q 1010128 PHOENIX CONTACT Connector for printed circuit board, number of poles:..

Brand: PHOENIX CONTACT | Manufacturer Part Number: FRONT-MC 1,5/ 8-STF-3,81BUBD1Q



Manufacturer	PHOENIX CONTACT
MPN / Reference	FRONT-MC 1,5/ 8-STF-3,81BUBD1Q
Catalog number	1010128
Category	Cable connector
Minimum order	50 Pcs
Document ID	EO-8CC0B4E2A9
Generated	2026-08-06

Product Overview

Connector for printed circuit board, number of poles: 8, pitch: 3,81 mm, type of connection: Connection by screw-on front, color: blue, surface contacts: Tin

Connector for printed circuit board, nominal section: 1.5 mm², colour: blue, rated current: 8 A, dimensioning voltage (III/2): 160 V, surface contacts: Tin, contact type: Connecting female, Number of potentials: 8, Number of rows: 1, Number of poles per row: 8, number of connections: 8, article family: FRONT-MC 1.5/.. -STF, pitch: 3.81 mm, connection type: Front screw connection, conductor/printed circuit board connection direction: 0°, Stecksystem:MINI COMBICON, Lock: Screw lock, packing type: boxed packaging

PCB connector, nominal cross section: 1.5 mm², color: blue, nominal current: 8 A, rated voltage (III/2): 160 V, contact surface: Tin, contact connection type: Socket, number of potentials: 8, number of rows: 1, number of positions: 8, number of connections: 8, product range: FRONT-MC 1,5/..-STF, pitch: 3.81 mm, connection method: Front screw connection, screw head form: L Slotted, conductor/PCB connection direction: 0 °, plug-in system: COMBICON MC 1,5, locking: Screw locking mechanism, mounting: Screw flange, type of packaging: packed in cardboard

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	PHOENIX CONTACT > PCB Connectors (PCC)
--------------	--

Additional Product Information

Technical dataProduct propertiesProduct line COMBICON Connectors S
Product type PCB connector

Product family FRONT-MC 1,5/..-STF

Number of positions 8

Pitch 3.81 mm

Number of connections 8

Number of rows 1

Number of potentials 8

Electrical propertiesNominal current IN 8 A

Nominal voltage UN 160 V

Degree of pollution 3

Contact resistance 1.6 mΩ

Rated voltage (III/3) 160 V

Rated surge voltage (III/3) 2.5 kV

Rated voltage (III/2) 160 V

Rated surge voltage (III/2) 2.5 kV

Rated voltage (II/2) 320 V

Rated surge voltage (II/2) 2.5 kV

Connection dataConnection technology

Type Standard

Connector system COMBICON MC 1,5

Nominal cross section 1.5 mm²

Contact connection type Socket

Interlock

Locking type Screw locking mechanism

Mounting flange Screw flange

Tightening torque 0.3 Nm

Conductor connection

Connection method Front screw connection

Conductor/PCB connection direction 0 °

Conductor cross section rigid 0.14 mm² ... 1.5 mm²

Conductor cross section flexible 0.14 mm² ... 1.5 mm²

Conductor cross section AWG 28 ... 16

Conductor cross section flexible, with ferrule without plastic sleeve 0.25 mm² ... 1.5 mm²

Conductor cross section, flexible, with ferrule, with plastic sleeve 0.25 mm² ... 0.5 mm²

2 conductors with same cross section, solid 0.14 mm² ... 0.5 mm²

2 conductors with same cross section, flexible 0.14 mm² ... 0.75 mm²

2 conductors with same cross section, flexible, with ferrule without plastic sleeve 0.25 mm² ... 0.34 mm²

2 conductors with the same cross section, flexible, with ferrule without plastic sleeve 0.25 mm² ... 0.34 mm²

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / FRONT-MC 1,5/ 8-STF-3,81BUBD1Q with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.