

INDUSTRIAL COMPONENT DATA

MACX MCR-SL-RPSSI-I 2865955 PHOENIX CONTACT

Power/input isolating amplifier

Brand: PHOENIX CONTACT | Manufacturer Part Number: MACX MCR-SL-RPSSI-I



Manufacturer	PHOENIX CONTACT
MPN / Reference	MACX MCR-SL-RPSSI-I
Catalog number	2865955
Category	Isolation amplifier
Minimum order	1 Pcs
Document ID	EO-0AF8C068D1
Generated	2026-08-02

Product Overview

Power/input isolating amplifier

Input and power signal conditioner, with HART transparency. It transmits 0/4-20 mA powered or active signals at a load (active or passive). 3-way galvanic separation, SIL 2 according to IEC 61508.

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > INTERFACE Components (IF)

Additional Product Information

Key Commercial Data

Orderkey 2865955

Packing unit 1 pc

Catalog page Page 120 (C-5-2017)

GTIN 4046356448314

Weight per Piece (excluding packing) 126.000 g

Custom tariff number 85437090

Country of origin DE (Germany)

Note

Utilization restriction 1

Dimensions

Width 12.5 mm

Height 112.5 mm

Depth 114.5 mm

Ambient conditions

Ambient temperature (operation) -20 °C ... 60 °C (Any mounting position)

Ambient temperature (storage/transport) -40 °C ... 80 °C

Maximum altitude ≤ 2000 m

Permissible humidity (operation) 10 % ... 95 % (non-condensing)

Noise immunity EN 61000-6-2 When being exposed to interference, there may be minimal deviations.

Input data

Signal input Active current input

Current input signal 4 mA ... 20 mA

Transmitter supply voltage > 21.5 V (20 mA)

> 20.8 V (24 mA)

Underload/overload signal range 0 mA ... 24 mA (Extended transmission range for diagnostics)

Signal input Passive current input

Current input signal 0 mA ... 20 mA

4 mA ... 20 mA

Voltage drop < 3.5 V (in input isolating amplifier operation)

Underload/overload signal range 0 mA ... 24 mA (Extended transmission range for diagnostics)

Output data

Signal output Current output (active and passive)

Current output signal 4 mA ... 20 mA (active)

4 mA ... 20 mA (14 ... 26 V ext. source voltage)

Transmission Behavior 1:1 to input signal

Load/output load current output < 1000 ? (20 mA)

< 825 ? (24 mA)

Output ripple < 20 mVrms

Output behavior in the event of an error 0 mA (Cable break in the input)

≥ 22.5 mA (Cable short-...)

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / MACX MCR-SL-RPSSI-I with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.