

INDUSTRIAL COMPONENT DATA

MACX MCR-SL-RPSSI-2I 2924825 PHOENIX CONTACT

Repeater power supply

Brand: PHOENIX CONTACT | Manufacturer Part Number: MACX MCR-SL-RPSSI-2I



Manufacturer	PHOENIX CONTACT
MPN / Reference	MACX MCR-SL-RPSSI-2I
Catalog number	2924825
Category	Isolation amplifier
Minimum order	1 Pcs
Document ID	EO-47B5B9D160
Generated	2026-08-04

Product Overview

Repeater power supply

HART Transparent Power Transducer Power Signal Conditioner and Input Signal Conditioner. Transfers 0/4 powered or activated signals... 20 mA galvanically separated from the field in two charges. 4-way galvanic separation, screw connection, SIL, PL.

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	PHOENIX CONTACT > INTERFACE Components (IF)
--------------	---

Additional Product Information

Key Commercial Data

Orderkey 2924825

Packing unit 1 pc

Catalog page Page 121 (C-5-2017)

GTIN 4046356572040

Weight per Piece (excluding packing) 156.000 g

Custom tariff number 85437090

Country of origin DE (Germany)

Note

Utilization restriction 1

Dimensions

Width 12.5 mm

Height 112.5 mm

Depth 114.5 mm

Ambient conditions

Ambient temperature (operation) -20 °C ... 60 °C (Any mounting position)

-20 °C ... 70 °C (any mounting position, module distance? 5 mm, MTBF reduction factor 2.5, not assessed by UL)

Ambient temperature (storage/transport) -40 °C ... 85 °C

Maximum altitude ≤ 2000 m

Permissible humidity (operation) 10 % ... 95 % (non-condensing)

Noise immunity EN 61000-6-2

Input data

Signal input Repeater power supply operation

Current input signal 4 mA ... 20 mA

Transmitter supply voltage > 21.5 V (20 mA)

> 21 V (23 mA)

Underload/overload signal range 0 mA ... 24 mA (Extended transmission range for diagnostics)

Signal input Signal conditioner operation

Current input signal 0 mA ... 20 mA

4 mA ... 20 mA

Voltage drop < 3.9 V (in input isolating amplifier operation)

Underload/overload signal range 0 mA ... 24 mA (Extended transmission range for diagnostics)

Output data

Signal output Repeater power supply operation

Current output signal 4 mA ... 20 mA (active)

0 mA ... 20 mA

Load/output load current output < 450 ? (20 mA)

< 380 ? (23 mA)

Output ripple < 20 mVrms

Output behavior in the event of an error 0 mA (Cable break in the input)

≥ 23 mA (Cable short-circuit in the input)

Sig...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / MACX MCR-SL-RPSSI-2I with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.