

INDUSTRIAL COMPONENT DATA

MH-B10-12-MULTI-66-PA-LG 1299362 PHOENIX CONTACT

Plates for cable passage, outer diameter of the cable: 5x 3..

Brand: PHOENIX CONTACT | Manufacturer Part Number: MH-B10-12-MULTI-66-PA-LG



Manufacturer	PHOENIX CONTACT
MPN / Reference	MH-B10-12-MULTI-66-PA-LG
Catalog number	1299362
Category	Gland plate for small distribution boards/switchgear cabinets
Minimum order	1 Pcs
Document ID	EO-7F7A133442
Generated	2026-08-03

Product Overview

Plates for cable passage, outer diameter of the cable: 5x 3 mm ... 7mm, 4x 5mm... 10mm, 2x 7mm... 13mm, 1x 9mm... 16 mm, material: TPE-SEBS (outer material), color: light gray, length: 107 mm, width: 56 mm, height: 19 mm

Cable feed-through plates

Cable Feed-Through Plates, Cable Outer Diameter: 5x 3 mm ... 7mm, 4x 5mm... 10 mm, 2x 7 mm ... 13 mm, 1x 9 mm ... 16 mm, Material: TPE-SEBS (Outer Material), Color: Light Grey, Length: 107 mm, Width: 56 mm, Height: 19 mm

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > Industrial plug-in connectors/interfaces

Additional Product Information

Technical dataNotesGeneral incl. fixing screws
Item PropertiesProduct Type Cable grommet frame
Connection dataTightening torque 1.8 Nm
DimensionsWidth 56 mm
Height 19 mm
Longitude 107 mm
Material DataMaterial TPE-SEBS
Flammability class according to UL 94 V0
Cable/LineCable Outer Diameter () 5x 3 mm ... 7 mm
4x 5 mm ... 10 mm
2x 7 mm ... 13 mm

1x 9 mm ... 16 mm

Environmental and life-life conditions Environmental conditions

Protection Index IP66

Ambient Temperature (Service) -40 °C ... 90 °C

assembly Installation instructions Set screw M4, torque: 1.8 Nm, inner hexagon wrench width 5

The fixing screws included in the packaging must be used for assembly.

Assembly sequence:

- 1) Fix the Multigates with the attached set screws (note the pair)
- 2) Tap the hole in the membrane (with a screwdriver) or cut off the tip of the cone
- 3) Guide the wire (from the outside) through the hole. Remove the cable about 20 mm (to improve traction compensation)

ETIM for 1299362 Distribution boards (EC000211)

Feature Name

Feature Value

Width (EF000008)

56 mm

Material (EF002169)

Other

Pre-stamping (EF001039)

No

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / MH-B10-12-MULTI-66-PA-LG with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.