

INDUSTRIAL COMPONENT DATA

MH-B24-23-MULTI-66-PA-LG 1299361 PHOENIX CONTACT

Plates for cable passage, outer diameter of the cable: 4x 1..

Brand: PHOENIX CONTACT | Manufacturer Part Number: MH-B24-23-MULTI-66-PA-LG



Manufacturer	PHOENIX CONTACT
MPN / Reference	MH-B24-23-MULTI-66-PA-LG
Catalog number	1299361
Category	Gland plate for small distribution boards/switchgear cabinets
Minimum order	1 Pcs
Document ID	EO-743CCBF204
Generated	2026-08-04

Product Overview

Plates for cable passage, outer diameter of the cable: 4x 1.5 mm ... 3mm, 4x 3.2mm... 6.3 mm, 10x 4 mm... 7.5 mm, 1x 5.5 mm... 10.5mm, 1x 8mm... 12.5 mm, material: TPE-SEBS (outer material), color: light gray, length: 154 mm, width: 56 mm, height: 19 mm

Cable feed-through plates

Cable feed-through plates, external cable diameter: 4x 1.5 mm ... 3 mm, 4x 3.2 mm ... 6.3 mm, 10x 4 mm ... 7.5 mm, 1x 5.5 mm ... 10.5 mm, 1x 8 mm ... 12.5 mm, material: TPE-SEBS (external material), color: light grey, length: 154 mm, width: 56 mm, height: 19 mm

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > Industrial plug-in connectors/interfaces

Additional Product Information

Technical dataNotesGeneral incl. mounting screws

Product propertiesProduct type Frame for cable sleeves

Connection dataTightening torque 1.8 Nm

DimensionsWidth 56 mm

Height 19 mm

Length 154 mm

Material specificationsMaterial TPE-SEBS

Flammability rating according to UL 94 V0

Cable/lineExternal cable diameter () 4x 1.5 mm ... 3 mm

4x 3.2 mm ... 6.3 mm

10x 4 mm ... 7.5 mm

1x 5.5 mm ... 10.5 mm

1x 8 mm ... 12.5 mm

3x 12 mm ... 16.2 mm

Environmental and real-life conditions Ambient conditions

Degree of protection IP66

Ambient temperature (operation) -40 °C ... 90 °C

Mounting Assembly instructions M4 mounting screw, torque: 1.8 Nm, SW5 Allen key

The mounting screws included should be used for assembly.

Assembly steps:

- 1) Fix Multigates with the mounting screws provided (observe torque)
- 2) Make a hole in the membrane (with a screwdriver) or cut off the tip of the cone
- 3) Guide the cable through the opening (from the outside). Withdraw the cable approximately 20 mm (to improve strain relief).

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / MH-B24-23-MULTI-66-PA-LG with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.