

INDUSTRIAL COMPONENT DATA

FRONT 2,5-V/SA10/ 9 1704907 PHOENIX CONTACT PCB terminal block, Nominal current: 24 A, Nom. voltage: 400 V, ..

Brand: PHOENIX CONTACT | Manufacturer Part Number: FRONT 2,5-V/SA10/ 9



Manufacturer	PHOENIX CONTACT
MPN / Reference	FRONT 2,5-V/SA10/ 9
Catalog number	1704907
Category	Printed circuit board terminal
Minimum order	20 Pcs
Document ID	EO-0A92FFE839
Generated	2026-08-02

Product Overview

PCB terminal block, Nominal current: 24 A, Nom. voltage: 400 V, Pitch: 5 mm, Number of positions: 9, Connection method: Front screw connection, Mounting: Wave soldering, Conductor/PCB connection direction: 90 °, Color: green, The article can be aligned to create different nos. of positions!

Terminal block for printed circuit board, nominal current: 24 A, nominal voltage (III/2): 400 V, nominal cross-section: 2.5 mm², number of potentials: 9, number of rows: 1, number of poles per row: 9, article family: FRONT 2.5-V/SA10, pitch: 5 mm, connection type: Front screw connection, mounting: Wave soldering, conductor connection direction/printed circuit board: 90 °, color: green, Pin arrangement: Linear pin arrangement, Pin length [P]: 5 mm, number of solder pins per potential: 2, packaging type: boxed. The item can be aligned with different numbers of poles!

Printed circuit board terminal, nominal current: 24 A, rated voltage (III/2): 400 V, nominal cross section: 2.5 mm², number of potentials: 9, number of rows: 1, number of positions per row: 9, product range: FRONT 2,5-V/SA10, pitch: 5 mm, connection method: Front screw connection, mounting: Wave soldering, conductor/PCB connection direction: 90 °, color: green, Pin layout: Linear pinning, Solder pin [P]: 5 mm, number of solder pins per potential: 2, type of packaging: packed in cardboard. The article can be aligned to create diff...

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > PCB Connectors (PCC)

Additional Product Information

Technical dataProduct propertiesProduct type Printed circuit board terminal

Product family FRONT 2,5-V/SA10

Product line COMBICON Terminals M

Type PC terminal block can be aligned

Number of positions 9

Pitch 5 mm

Number of connections 9

Number of rows 1

Number of potentials 9

Pin layout Linear pinning

Solder pins per potential 2

Data management status

Article revision 05

Electrical propertiesNominal current IN 24 A

Nominal voltage UN 400 V

Rated voltage (III/3) 250 V

Rated surge voltage (III/3) 4 kV

Rated voltage (III/2) 400 V

Rated surge voltage (III/2) 4 kV

Rated voltage (II/2) 630 V

Rated surge voltage (II/2) 4 kV

Connection dataConnection technology

Type PC terminal block can be aligned

Nominal cross section 2.5 mm²

Conductor connection

Connection method Front screw connection

Conductor cross section rigid 0.2 mm² ... 2.5 mm²

Conductor cross section flexible 0.2 mm² ... 2.5 mm²

Conductor cross section AWG 24 ... 14

Conductor cross section flexible, with ferrule without plastic sleeve 0.25 mm² ... 1.5 mm²

Conductor cross section, flexible, with ferrule, with plastic sleeve 0.25 mm² ... 1.5 mm²

2 conductors with same cross section, solid 0.2 mm² ... 0.75 mm²

2 conductors with same cross section, flexible 0.2 mm² ... 0.75 mm²

2 conductors with same cross section, flexible, with ferrule without plastic sleeve 0.25 mm² ... 0.34 mm²

Stripping length 9 mm

Tightening torque 0.4 Nm ... 0.5 Nm

MountingMounting type Wave soldering

Pin layout Linear pinning

Material specificationsMa...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / FRONT 2,5-V/SA10/ 9 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.