

INDUSTRIAL COMPONENT DATA

QUINT4-SYS-PS/1AC/24DC/2.5/SC 2904614 PHOENIX CONTACT QUINT POWER primary switching power supply, screw conn..

Brand: PHOENIX CONTACT | Manufacturer Part Number: QUINT4-SYS-PS/1AC/24DC/2.5/SC



Manufacturer	PHOENIX CONTACT
MPN / Reference	QUINT4-SYS-PS/1AC/24DC/2.5/SC
Catalog number	2904614
Category	DC-power supply
Minimum order	1 Pcs
Document ID	EO-689B66E56B
Generated	2026-08-05

Product Overview

QUINT POWER primary switching power supply, screw connection, DIN rail mounting, device supply possible via TBUS DIN rail connectors, protective paint, input: single-phase, output: 24 V DC/2.5 A

Primary switched power supplies, QUINT POWER, Screw connection, Rail mount, input: 1 phase, output: 24 V DC / 2.5 A

Primary-switched power supply, QUINT POWER, screw connection, DIN rail mounting, supply of devices possible via the TBUS DIN rail connector, protective coating, input: single-phase, output: 24 V DC/2.5 A

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > Power Supplies (PS)

Additional Product Information

Technical dataInput dataAC operation

Nominal input voltage range 100 V AC ... 240 V AC

Input voltage range 100 V AC ... 240 V AC -15 % ... +10 %

Electric strength, max. 300 V AC 30 s

Typical national grid voltage 120 V AC

230 V AC

Voltage type of supply voltage AC/DC

Inrush current typ. 10 A (at 25 °C)

Inrush current integral (I2t) typ. 0.1 A2s

Inrush current limitation 10 A
Frequency range (fN) 50 Hz ... 60 Hz $\pm 10\%$
16.7 Hz (acc. to EN 50163)
Mains buffering time typ. 31 ms (120 V AC)
typ. 31 ms (230 V AC)
Current consumption 0.85 A (100 V AC)
0.7 A (120 V AC)
0.39 A (230 V AC)
0.37 A (240 V AC)
Protective circuit Transient surge protection; Varistor
Typical response time 500 ms
Input fuse 4 A (slow-blow, internal)
Recommended breaker for input protection 6 A ... 16 A (Characteristic B, C, D, K or comparable)
Discharge current to PE < 0.25 mA (264 V AC, 60 Hz)
 < 0.22 mA
DC operation
Input voltage range 110 V DC ... 250 V DC -20% ... $+40\%$
Voltage type of supply voltage AC/DC
Current consumption 0.75 A (110 V DC)
0.33 A (250 V DC)
Output data Efficiency typ. 93 % (120 V AC)
typ. 94 % (230 V AC)
Nominal output voltage 24 V DC
Setting range of the output voltage (USet) 24 V DC ... 27 V DC (constant capacity)
Nominal output current (IN) 2.5 A
Static Boost (IStat.Boost) 3.125 A ($\leq 40^\circ\text{C}$)
Dynamic Boost (IDyn.Boost) 4 A ($\leq 60^\circ\text{C}$ (on ≤ 5 s/off ≥ 5 s))
Feedback voltage resistance ≤ 32 V DC
Protection against overvoltage at the output (OVP) ≤ 30 V DC $\pm 2\%$
Control deviation $< 0.5\%$ (St...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / QUINT4-SYS-PS/1AC/24DC/2.5/SC with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.