

INDUSTRIAL COMPONENT DATA

STEP3-PS/1AC/5DC/3/PT/USB-A 1335699 PHOENIX CONTACT

Primary switching power supplies, STEP POWER, Push-in co..

Brand: PHOENIX CONTACT | Manufacturer Part Number: STEP3-PS/1AC/5DC/3/PT/USB-A



Manufacturer	PHOENIX CONTACT
MPN / Reference	STEP3-PS/1AC/5DC/3/PT/USB-A
Catalog number	1335699
Category	DC-power supply
Minimum order	1 Pcs
Document ID	EO-EE0769FAA5
Generated	2026-08-03

Product Overview

Primary switching power supplies, STEP POWER, Push-in connection, Rail and direct mounting, Integrated cable slot with strain relief, input: 1 phase, output: 5 V DC / 3 A, USB-A up to 15 W

Primary Switching Power Supplies, STEPPOWER, Push-in Connection, Rail Mount, Input: 1-Phase, Output: 5 VDC / 3 A

Primary-switched power supply unit, STEP POWER, Push-in connection, DIN rail or direct mounting, Integrated cable groove with strain relief, input: 1-phase, output: 5 V DC / 3 A, USB-A up to 15 W

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > Power Supplies (PS)

Additional Product Information

Technical dataInput dataAC operation

Supply system configuration Star network (TN, TT, IT (PE))

Input voltage range 100 V AC ... 240 V AC -15 % ... +10 %

Typical national grid voltage 120 V AC

230 V AC

Voltage type of supply voltage AC

Inrush current typ. 30 A (25 °C)

Inrush current integral (I_{2t}) typ. 0.14 A²sFrequency range (f_N) 50 Hz ... 60 Hz ±10 %

Mains buffering time typ. 18 ms (120 V AC)

typ. 80 ms (230 V AC)

Current consumption 0.3 A (100 V AC)
0.14 A (240 V AC)
Switch-on time typ. 2 s
Device mains fuse 1.25 A internal (device protection), slow-blow
Recommended breaker for input protection 6 A ... 16 A (Characteristics B, C, D, K)
Discharge current to PE < 0.25 mA
DC operation
Input voltage range 110 V DC ... 250 V DC -20 % ... +10 %
Voltage type of supply voltage DC
Current consumption 0.17 A (110 V DC)
0.07 A (250 V DC)
Output dataEfficiency > 81.5 % (120 V AC)
> 82 % (230 V AC)
Nominal output voltage 5 V DC
Nominal output current (IN) 3 A
Short-circuit-proof yes
No-load proof yes
Derating > 50 °C ... 70 °C (2 % / K)
Crest factor typ. 3.3
typ. 4.2
Output power (PN) 15 W
Connection in parallel yes, for increasing power and redundancy with diode
Connection in series yes, for increased output voltage
Feedback voltage resistance <= 10 V DC
Protection against overvoltage at the output (OVP) < 10 V DC
Residual ripple typ. 80 mVPP
Control deviation < 1.5 % (Static load change 10 % ... 90 %)
< 5 % (Dynamic load change 10 % ... 90 %, (10 Hz))
< 0.1 % (change in input voltag...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / STEP3-PS/1AC/5DC/3/PT/USB-A with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.