

INDUSTRIAL COMPONENT DATA

590.FEM4003 SCAME SWITCH DISCONNECTOR 40A 3P IP65

Brand: SCAME | Manufacturer Part Number: 590.FEM4003



Manufacturer	SCAME
MPN / Reference	590.FEM4003
Catalog number	10000
Category	Switch disconnecter
Minimum order	1 Pcs
Document ID	EO-0FA2A4F412
Generated	2026-07-28

Product Overview

SWITCH DISCONNECTOR 40A 3P IP65

MANOEUVRING INT. 40A 3P IP65

40A 3P IP65 168x192x80mm FR1 IK08 EMERGENCY YELLOW/RED FIRE RATED

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path SCAME > Switches - SCAME

Additional Product Information

Commercial SeriesISOLATORS-FR SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeEnclosedMounting versionSURFACE MOUNTINGMaterialDIE-CAST ALUMINIUMProtection degree IP65Installation temperature-25°C/+60°CTypeEMERGENCYColourYELLOW/REDRated current40APoles3PSwitch sizeFR1Rated voltage690VDimensions168x192x80mmNotesFIRE RATEDFire rated classF400 (120min)Protection degree IKIK08Rated insulation voltage (Ui)690VACRated impulse voltage (Uimp)6KVThermal current (Ithe)40ACurrent (Ie) in AC21A (415V)40ACurrent (Ie) in AC22A (415V)40ACurrent (Ie) in AC23A (415V)35APower AC23A (415V)18.5kWShort-time current400Alcw(1s)Conditional short circuit cur.10kAeffAssociate fuse - type gG40ATerminals - Flexible wires1.5-10mm²Terminals - Rigid wires1.5-16mm²Catalogue notesHandle padlockable in OFF (3 padlocks) and ON (1 padlock) positionEquipped with door interlockBlank sidesUnswitched neutral (solid neutral terminal block)

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.FEM4003 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.