

INDUSTRIAL COMPONENT DATA

590.YA1008B SCAME SWITCH DISCONNECTOR 100A 8P B

Brand: SCAME | Manufacturer Part Number: 590.YA1008B



Manufacturer	SCAME
MPN / Reference	590.YA1008B
Catalog number	10000
Category	Switch disconnector
Minimum order	1 Pcs
Document ID	EO-4E0257D26C
Generated	2026-08-01

Product Overview

SWITCH DISCONNECTOR 100A 8P B
BODY INT. MANEUVER 100A 8P B
100A 8P Y4 BOX (B)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path SCAME > Switches - SCAME

Additional Product Information

Commercial SeriesCOMMAND SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeOpen
typeMounting versionBMaterialTHERMOPLASTICInstallation temperature-25°C/+60°CTypeBOX (B)Rated
current100APoles8PSwitch sizeY4Rated voltage690VRated insulation voltage (Ui)690VACRated impulse voltage
(Uimp)8kVThermal current (Ithe)125ACurrent (Ie) in AC21A (415V)125ACurrent (Ie) in AC21A (500V)125ACurrent (Ie) in
AC21A (690V)125ACurrent (Ie) in AC22A (415V)100ACurrent (Ie) in AC22A (500V)100ACurrent (Ie) in AC22A
(690V)100ACurrent (Ie) in AC23A (415V)100ACurrent (Ie) in AC23A (500V)63ACurrent (Ie) in AC23A (690V)63APower
AC23A (415V)46kWShort-time current1,5kA Icw(1s)Conditional short circuit cur.30kAeffAssociate fuse - type
gG100ATerminals - Flexible wires10-50mm²Terminals - Rigid wires10-50mm²Catalogue notesEquipped with direct
handleWith late break and early make neutral poleBOX (B) = Base mountingDIN rail / screw fixing

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.YA1008B with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.