

INDUSTRIAL COMPONENT DATA

590.YA1605B-C SCAME CHANGE OVER SWITCH 160A 3P+N B

Brand: SCAME | Manufacturer Part Number: 590.YA1605B-C



Manufacturer	SCAME
MPN / Reference	590.YA1605B-C
Catalog number	10000
Category	Switch disconnecter
Minimum order	1 Pcs
Document ID	EO-27A020E686
Generated	2026-08-03

Product Overview

CHANGE OVER SWITCH 160A 3P+N B
INT. BODY MANEUVER 160A 3P+N B
160A 3P+N C3 BOX (B)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	SCAME > Switches - SCAME
--------------	--------------------------

Additional Product Information

Commercial SeriesCOMMAND SeriesSynthetical descriptionCHANGE OVER SWITCHConstruction typeOpen
typeMounting versionBMaterialTHERMOPLASTICInstallation temperature-25°C/+60°CTypeBOX (B)Rated
current160APoles3P+NSwitch sizeC3Rated voltage690VRated insulation voltage (Ui)800VACRated impulse voltage
(Uimp)8kVThermal current (Ithe)160ACurrent (Ie) in AC21A (415V)160ACurrent (Ie) in AC21A (500V)160ACurrent (Ie) in
AC21A (690V)160ACurrent (Ie) in AC22A (415V)160ACurrent (Ie) in AC22A (500V)160ACurrent (Ie) in AC22A
(690V)125ACurrent (Ie) in AC23A (415V)160ACurrent (Ie) in AC23A (500V)125ACurrent (Ie) in AC23A (690V)125APower
AC23A (415V)69kWShort-time current3kA Icw(1s)Conditional short circuit cur.50kAeffAssociate fuse - type
gG125ATerminals - Flexible wires10-70mm²Terminals - Rigid wires10-70mm²Catalogue notesEquipped with direct
handleWith late break and early make neutral poleBOX (B) = Base mountingHandle padlockable in OFF position (1
padlock)

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.YA1605B-C with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.