

INDUSTRIAL COMPONENT DATA

590.YA1608B SCAME SWITCH DISCONNECTOR 160A 8P B

Brand: SCAME | Manufacturer Part Number: 590.YA1608B



Manufacturer	SCAME
MPN / Reference	590.YA1608B
Catalog number	10000
Category	Switch disconnecter
Minimum order	1 Pcs
Document ID	EO-89350DA018
Generated	2026-08-05

Product Overview

SWITCH DISCONNECTOR 160A 8P B
BODY INT. MANEUVER 160A 8P B
160A 8P Y5 BOX (B)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path SCAME > Switches - SCAME

Additional Product Information

Commercial SeriesCOMMAND SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeOpen
typeMounting versionBMaterialTHERMOPLASTICInstallation temperature-25°C/+60°CTypeBOX (B)Rated
current160APoles8PSwitch sizeY5Rated voltage690VRated insulation voltage (Ui)690VACRated impulse voltage
(Uimp)8kVThermal current (Ithe)160ACurrent (Ie) in AC21A (415V)160ACurrent (Ie) in AC21A (500V)160ACurrent (Ie) in
AC21A (690V)160ACurrent (Ie) in AC22A (415V)160ACurrent (Ie) in AC22A (500V)160ACurrent (Ie) in AC22A
(690V)125ACurrent (Ie) in AC23A (415V)160ACurrent (Ie) in AC23A (500V)125ACurrent (Ie) in AC23A (690V)125APower
AC23A (415V)69kWShort-time current3kA Icw(1s)Conditional short circuit cur.50kAeffAssociate fuse - type
gG125ATerminals - Flexible wires10-70mm²Terminals - Rigid wires10-70mm²Catalogue notesEquipped with direct
handleWith late break and early make neutral poleBOX (B) = Base mountingDIN rail / screw fixing

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.YA1608B with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.