

INDUSTRIAL COMPONENT DATA**590.YA325B-C SCAME CHANGE OVER SWITCH 32A 3P+N B**

Brand: SCAME | Manufacturer Part Number: 590.YA325B-C



Manufacturer	SCAME
MPN / Reference	590.YA325B-C
Catalog number	10000
Category	Switch disconnecter
Minimum order	1 Pcs
Document ID	EO-DEF243B3C9
Generated	2026-08-02

Product Overview

CHANGE OVER SWITCH 32A 3P+N B
BODY INT. MANEUVER 32A 3P+N B
32A 3P+N C1 BOX (B)

STRUCTURED PRODUCT DATA**Technical Specifications**

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path SCAME > Switches - SCAME

Additional Product Information

Commercial SeriesCOMMAND SeriesSynthetical descriptionCHANGE OVER SWITCHConstruction typeOpen
typeMounting versionBMaterialTHERMOPLASTICInstallation temperature-25°C/+60°CTypeBOX (B)Rated
current32APoles3P+NSwitch sizeC1Rated voltage690VRated insulation voltage (Ui)800VACRated impulse voltage
(Uimp)8kVThermal current (Ithe)40ACurrent (Ie) in AC21A (415V)40ACurrent (Ie) in AC21A (500V)40ACurrent (Ie) in
AC21A (690V)40ACurrent (Ie) in AC22A (415V)32ACurrent (Ie) in AC22A (500V)32ACurrent (Ie) in AC22A
(690V)32ACurrent (Ie) in AC23A (415V)32ACurrent (Ie) in AC23A (500V)32ACurrent (Ie) in AC23A (690V)25APower
AC23A (415V)15kWShort-time current1,1kA Icw(1s)Conditional short circuit cur.50kAeffAssociate fuse - type
gG32ATerminals - Flexible wires2.5-16mm²Terminals - Rigid wires2.5-16mm²Catalogue notesEquipped with direct
handleWith late break and early make neutral poleBOX (B) = Base mountingHandle padlockable in OFF position (1
padlock)

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.YA325B-C with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.