

INDUSTRIAL COMPONENT DATA

590.YA328B SCAME SWITCH DISCONNECTOR 32A 8P B

Brand: SCAME | Manufacturer Part Number: 590.YA328B



Manufacturer	SCAME
MPN / Reference	590.YA328B
Catalog number	10000
Category	Switch disconnecter
Minimum order	1 Pcs
Document ID	EO-9390F7E1C6
Generated	2026-08-02

Product Overview

SWITCH DISCONNECTOR 32A 8P B
BODY INT. MANEUVER 32A 8P B
32A 8P Y3 BOX (B)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	SCAME > Switches - SCAME
--------------	--------------------------

Additional Product Information

Commercial SeriesCOMMAND SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeOpen typeMounting versionBMaterialTHERMOPLASTICInstallation temperature-25°C/+60°CTypeBOX (B)Rated current32APoles8PSwitch sizeY3Rated voltage690VRated insulation voltage (Ui)690VACRated impulse voltage (Uimp)8kVThermal current (Ithe)40ACurrent (Ie) in AC21A (415V)40ACurrent (Ie) in AC21A (500V)40ACurrent (Ie) in AC21A (690V)40ACurrent (Ie) in AC22A (415V)32ACurrent (Ie) in AC22A (500V)32ACurrent (Ie) in AC22A (690V)32ACurrent (Ie) in AC23A (415V)32ACurrent (Ie) in AC23A (500V)32ACurrent (Ie) in AC23A (690V)25APower AC23A (415V)15kWShort-time current1,1kA Icw(1s)Conditional short circuit cur.50kAeffAssociate fuse - type gG32ATerminals - Flexible wires2.5-16mm²Terminals - Rigid wires2.5-16mm²Catalogue notesEquipped with direct handleWith late break and early make neutral poleBOX (B) = Base mountingDIN rail / screw fixing

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.YA328B with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.