

**INDUSTRIAL COMPONENT DATA**

# 1SDA059266R1 ABB E2N 1000 PR121/P-LSIG In 1000A 3p W MP

Brand: ABB | Manufacturer Part Number: 1SDA059266R1



|                 |                                                                   |
|-----------------|-------------------------------------------------------------------|
| Manufacturer    | ABB                                                               |
| MPN / Reference | 1SDA059266R1                                                      |
| Catalog number  | 059266                                                            |
| Category        | Power circuit-breaker for trafo/generator/installation protection |
| Minimum order   | 1 Pcs                                                             |
| Document ID     | EO-1763121DFB                                                     |
| Generated       | 2026-08-01                                                        |

## Product Overview

E2N 1000 PR121/P-LSIG In=1000A 3p W MP

E2N1000 PR121/P LSIG 3P W MP

**STRUCTURED PRODUCT DATA**

## Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

## Classification & Catalog Path

Catalog path      **ABB > Service Breakers**

## Additional Product Information

Material Compliance

REACH Declaration 9AKK108466A1425

RoHS Declaration 9AKK108466A1424

RoHS Information Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

Conflict Minerals Reporting Template (CMRT) Document availability on demand

Environmental

Environmental Information 9AKK10103A6076

Ordering

EAN 8015644616274

Minimum Order Quantity 1 piece

Customs Tariff Number 85362090

Dimensions

Product Net Width 324 mm

Product Net Height 461 mm

Product Net Depth / Length 396.5 mm

Product Net Weight 49 kg

Container Information

Package Level 1 Units 1 piece

Package Level 1 Width 515 mm

Package Level 1 Height 600 mm

Package Level 1 Depth / Length 515 mm

Package Level 1 Gross Weight 59 kg

Package Level 1 EAN 8015644609139

Additional Information

Product Main Type SACE Emax

Product Name Air Circuit Breaker

Product Type Air Circuit Breaker

Version W

Technical

Current Type AC

Electrical Durability  $U_e \leq 440$  V 15000 cycle

$U_e = 500 \dots 690$  V 15000 cycle

30 cycles per hour

Mechanical Durability 25000 cycle

60 cycles per hour

Number of Poles 3P

Power Loss 83.2 W

Rated Current ( $I_n$ ) 1000 A

Rated Impulse Withstand Voltage ( $U_{imp}$ ) 12 kV

Rated Insulation Voltage ( $U_i$ ) 1000 V

Rated Operational Current ( $I_e$ ) 1000 A

Rated Operational Voltage 690 V AC

Rated Service Short-Circuit Breaking Capacity ( $I_{cs}$ ) (220 V AC) 65 kA

(230 V AC) 65 kA

(380 V AC) 65 kA

(400 V AC) 65 kA

(415 V AC) 65 kA

(440 V AC) 65 kA

(500 V AC) 55 kA

(660 V AC) 55 kA

(690 V AC) 55 kA

Rated Short-time Withstand Current Low...

## REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send ABB / 1SDA059266R1 with the required quantity to [info@electricaonline.com](mailto:info@electricaonline.com) or use [electricaonline.com/request-quote](https://electricaonline.com/request-quote).

### GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.