

**INDUSTRIAL COMPONENT DATA**

# 1SDA056681R1 ABB E3V 2500 PR121/P-LSI In 2500A 4p W MP

Brand: ABB | Manufacturer Part Number: 1SDA056681R1



|                 |                                                                   |
|-----------------|-------------------------------------------------------------------|
| Manufacturer    | ABB                                                               |
| MPN / Reference | 1SDA056681R1                                                      |
| Catalog number  | 056681                                                            |
| Category        | Power circuit-breaker for trafo/generator/installation protection |
| Minimum order   | 1 Pcs                                                             |
| Document ID     | EO-BEAC6891FF                                                     |
| Generated       | 2026-08-03                                                        |

## Product Overview

E3V 2500 PR121/P-LSI In=2500A 4p W MP

E3V2500 PR121/P LSI 4P W MP

**STRUCTURED PRODUCT DATA**

## Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

## Classification & Catalog Path

Catalog path      ABB &gt; Rack "Megamax-Emax" &gt; E3

## Additional Product Information

**Material Compliance**

REACH Declaration 9AKK108466A1425

RoHS Declaration 9AKK108466A1424

RoHS Information Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019

Conflict Minerals Reporting Template (CMRT) Document availability on demand

**Environmental**

Environmental Information 9AKK10103A6076

**Ordering**

EAN 8015644580216

Minimum Order Quantity 1 piece

Customs Tariff Number 85362090

**Dimensions**

Product Net Width 558 mm

Product Net Height 461 mm

Product Net Depth / Length 396.5 mm

Product Net Weight 81 kg

Container Information

Package Level 1 Units 1 piece

Package Level 1 Width 515 mm

Package Level 1 Height 600 mm

Package Level 1 Depth / Length 785 mm

Package Level 1 Gross Weight 96 kg

Package Level 1 EAN 8015644580216

Additional Information

Product Main Type SACE Emax

Product Name Air Circuit Breaker

Product Type Air Circuit Breaker

Version W

Technical

Current Type AC

Electrical Durability  $U_e \leq 440 \text{ V}$  8000 cycle

$U_e = 500 \dots 690 \text{ V}$  7000 cycle

20 cycles per hour

Mechanical Durability 20000 cycle

60 cycles per hour

Number of Poles 4P

Power Loss 350 W

Rated Current ( $I_n$ ) 2500 A

Rated Impulse Withstand Voltage ( $U_{imp}$ ) 12 kV

Rated Insulation Voltage ( $U_i$ ) 1000 V

Rated Operational Current ( $I_e$ ) 2500 A

Rated Operational Voltage 690 V AC

Rated Service Short-Circuit Breaking Capacity ( $I_{cs}$ ) (220 V AC) 100 kA

(230 V AC) 100 kA

(380 V AC) 100 kA

(400 V AC) 100 kA

(415 V AC) 100 kA

(440 V AC) 100 kA

(500 V AC) 85 kA

(660 V AC) 85 kA

(690 V AC) 85 kA

Rated Short-time Withstand Current....

## REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send ABB / 1SDA056681R1 with the required quantity to [info@electricaonline.com](mailto:info@electricaonline.com) or use [electricaonline.com/request-quote](https://electricaonline.com/request-quote).

### GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.