

INDUSTRIAL COMPONENT DATA

1SFA897111R7000 ABB Soft Starter 230V/40kW, 400V/75kW, 500V/90kW, 143A

Brand: ABB | Manufacturer Part Number: 1SFA897111R7000



Manufacturer	ABB
MPN / Reference	1SFA897111R7000
Catalog number	897111
Category	Soft starter
Minimum order	1 Pcs
Document ID	EO-A671620F28
Generated	2026-08-01

Product Overview

Soft Starter 230V/40kW, 400V/75kW, 500V/90kW, 143A
SOFT RACKER PSE170-600-70
PSE170-600-70 Softstarter - 171 A - 208 ... 600 V AC

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path **ABB > Soft Starters > starters PSE**

Additional Product Information

Ordering

Minimum Order Quantity 1 piece

Customs Tariff Number 85371091

Popular Downloads

Data Sheet, Technical Information 1SFC132012C0201

Instructions and Manuals 1SFC132427M0201

Instructions and Manuals (Part 2) 1SFC132057M0201

Instructions and Manuals (Part 3) 1SFC132060M0201

CAD Dimensional Drawing 2CDC001079B0201

EPLAN Data 9AAC170220_EPLAN

Wiring Diagram N/A

Dimensions

Product Net Width 130 mm

Product Net Height 295 mm

Product Net Depth / Length 220 mm

Product Net Weight 4.4 kg

Technical

Rated Operational Voltage 208 ... 600 V AC

Rated Control Supply Voltage (Us) 100 ... 250 V AC

Rated Control Circuit Voltage (Uc) 24 V DC

Rated Frequency (f) 50/60 Hz

Main Circuit 50 / 60 Hz

Rated Operational Power - In-Line Connection (Pe) (230 V) 45 kW

(400 V) 90 kW

(500 V) 110 kW

Rated Operational Current - In-Line Connection (Ie) 171 A

Service Factor Percentage 100 %

Overload Protection Build-in electronic overload protection

Integrated Electronic Overload Yes

Starting Capacity at Maximum Rated Current Ie 4xIe for 10s

Ramp Time 0 ... 30 second [unit of time]

1 ... 30 second [unit of time]

Initial Voltage During Start 30 ... 70 %

Step Down Voltage Special Ramp No %

Current Limit Function 1.5 ... 7xIe

Switch for Inside Delta Connection No

Run Signal Relay Yes

By-pass Signal Relay Yes

Fault Signal Relay Yes

Overload Signal Relay Yes

Analog Outputs 4...20 mA

Signal Indication Completed Start Ramp (LED) Green

Signal Indication Ready to Start/Standby ON (LED) Green

Signal Indication Running...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send ABB / 1SFA897111R7000 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.