

INDUSTRIAL COMPONENT DATA

1SFA896106R7000 ABB Soft Starter 230V/3kW, 400V/5,5kW, 500V/5,5kW, 12A

Brand: ABB | Manufacturer Part Number: 1SFA896106R7000



Manufacturer	ABB
MPN / Reference	1SFA896106R7000
Catalog number	896106
Category	Soft starter
Minimum order	1 Pcs
Document ID	EO-B1B3F91142
Generated	2026-07-29

Product Overview

Soft Starter 230V/3kW, 400V/5,5kW, 500V/5,5kW, 12A
 PSR12-600-70 ARR. SOFT 5.5kW 100-240Vac
 PSR12-600-70 Softstarter - 12 A - 208 ... 600 V AC

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path **ABB > Soft Starters > PSR**

Additional Product Information

Ordering

Minimum Order Quantity 1 piece

Customs Tariff Number 85371091

Popular Downloads

Data Sheet, Technical Information 1SFC132012C0201

Instructions and Manuals 1SFC132030M0001

Instructions and Manuals (Part 3) 1SFC132060M0201

CAD Dimensional Drawing 2CDC001079B0201

EPLAN Data 9AAC129235_EPLAN

Wiring Diagram N/A

Dimensions

Product Net Width 114 mm

Product Net Height 140 mm

Product Net Depth / Length 45 mm

Product Net Weight 0.4 kg

Technical

Rated Operational Voltage 208 ... 600 V AC

Rated Control Supply Voltage (Us) 100 ... 240 V AC

Rated Control Circuit Voltage (Uc) 24 V DC

Rated Frequency (f) 50/60 Hz

Main Circuit 50 / 60 Hz

Rated Operational Power - In-Line Connection (Pe) (230 V) 3 kW

(400 V) 5.5 kW

(500 V) 5.5 kW

Rated Operational Current - In-Line Connection (Ie) 12 A

Service Factor Percentage 100 %

Overload Protection Recommended MS132 10.00 ... 16.00

Integrated Electronic Overload No

Starting Capacity at Maximum Rated Current Ie 4xIe for 6s

Ramp Time 0 ... 20 second [unit of time]

1 ... 10 second [unit of time]

Initial Voltage During Start 40 ... 70 %

Step Down Voltage Special Ramp 100 ... 60 %

Current Limit Function No

Switch for Inside Delta Connection No

Run Signal Relay Yes

By-pass Signal Relay No

Fault Signal Relay No

Overload Signal Relay No

Signal Indication Completed Start Ramp (LED) Green

Signal Indication Ready to Start/Standby ON (LED) Green

Signal Indication Running R (LED) Green

Signal Indication Ramping Up/Down (LED) Green

Number of Starts Per Hour a...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send ABB / 1SFA896106R7000 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.