

INDUSTRIAL COMPONENT DATA

CTD5S1251AXXX CARLO GAVAZZI Primary current: 50-150A , Primary type: Split-core , Secondary current: 1A ,

..

Brand: CARLO GAVAZZI | Manufacturer Part Number: CTD5S1251AXXX



Manufacturer	CARLO GAVAZZI
MPN / Reference	CTD5S1251AXXX
Catalog number	10000
Category	Current transformer
Minimum order	1 Pcs
Document ID	EO-7561FEC08F
Generated	2026-08-03

Product Overview

Primary current: 50-150A , Primary type: Split-core , Secondary current: 1A , Primary current: 125A, Max bus bar size: 26x32mm , Mounting: DIN-rail, Panel, Bus-bar
Current Transformer
Split core Current transformer 125A/1A

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	CARLO GAVAZZI > Controls > Digital Panel Meters and temperature
--------------	---

Additional Product Information

Specifications

Rated primary current125 AOutput1 AHole diameter26 mm (1.02 in)Max busbar width26 mm (1.02 in)Accuracy class1
ETIM for CTD5S1251AXXX Low-voltage industrial controls and switchgear (EC002048)

Feature Name

Feature Value

Model (EF000010)

Attachable current transformer

Rated primary current (EF007405)

125 A

Rated secondary current (EF007471)

1 A

Rated secondary apparent power (EF007470)

1 VA

Opening diameter (EF005153)

26.7 mm

Number of primary inputs (EF006947)

1

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send CARLO GAVAZZI / CTD5S1251AXXX with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.