

INDUSTRIAL COMPONENT DATA

CTV8X800A333MV CARLO GAVAZZI Selected parameters

PRIMARY CURRENT 600...1200A PRIMARY TYPE Split-core

SECONDA..

Brand: CARLO GAVAZZI | Manufacturer Part Number: CTV8X800A333MV



Manufacturer	CARLO GAVAZZI
MPN / Reference	CTV8X800A333MV
Catalog number	6001200
Category	Current transformer
Minimum order	1 Pcs
Document ID	EO-3FE42818D4
Generated	2026-08-04

Product Overview

Selected parameters PRIMARY CURRENT 600...1200A PRIMARY TYPE Split-core SECONDARY CURRENT 0.333V
Others PRIMARY CURRENT 800A MAX BUS BAR SIZE 50x89mm MOUTING DIN-rail, Panel, Bus-bar
Current transformer, split core, compatible with EM21072MV analyzer, Max.50x89mm plate
Split core Current sensor 800A/333mV

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path **CARLO GAVAZZI > Controls > Digital Panel Meters and temperature**

Additional Product Information

Specifications

Rated primary current800 AOutput333 mVHole diameter50 mm (1.97 in)Max busbar width50 mm (1.97 in)Accuracy class1
ETIM for CTV8X800A333MV Low-voltage industrial controls and switchgear (EC002048)

Feature Name

Feature Value

Model (EF000010)

Attachable current transformer

Rated primary current (EF007405)

800 A

Opening diameter (EF005153)

50 mm

Number of primary inputs (EF006947)

1

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send CARLO GAVAZZI / CTV8X800A333MV with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.