

INDUSTRIAL COMPONENT DATA

15.5KV 71AMP 2.5" OIL FUSE 15.5OHGMA71 15-5OHGMA71 EATON ELECTRIC cartridge fuse Oil, MT, 71 A, AC 15.5 kV, ..

Brand: EATON - MOELLER | Manufacturer Part Number: 15.5KV 71AMP 2.5" OIL FUSE



Manufacturer	EATON - MOELLER
MPN / Reference	15.5KV 71AMP 2.5" OIL FUSE
Catalog number	15-5OHGMA71
Category	Medium-/high voltage fuse
Minimum order	3 Pcs
Document ID	EO-A6DC98AF82
Generated	2026-08-06

Product Overview

cartridge fuse Oil, MT, 71 A, AC 15.5 kV, BS2692 F02, 63.5 x 359 mm, back-up, BS, IEC, ESI, with striker

15.5KV 71AMP 2.5" OIL FUSE

15.5KV 71AMP 2.5" OIL FUSE - Oil fuse-link, medium voltage, 71 A, AC 15.5 kV, 40 kA, BS2692 F02, 63.5 x 359 mm, back-up, BS, IEC, ESI, with striker, oil-tight

Fuse, Oil fuse-link, medium voltage, 71 A, AC 15.5 kV, BS2692 F02, 63.5 x 359 mm, back-up, BS, IEC, ESI, with striker, cylindrical, oil-tight, protection of primary side transformer, and oil-filled fuse switch combination unit, BS2692-1, IEC 60282-1, ESI 12-8, Breaking Capacity 40 kA

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path

EATON - MOELLER > Busmann Series Medium Voltage fuses and accessories

Additional Product Information

Oil fuse-link, medium voltage, 71 A, AC 15.5 kV, 40 kA, BS2692 F02, 63.5 x 359 mm, back-up, BS, IEC, ESI, with striker, oil-tight
Fuse, Oil fuse-link, medium voltage, 71 A, AC 15.5 kV, BS2692 F02, 63.5 x 359 mm, back-up, BS, IEC, ESI, with striker, cylindrical, oil-tight, protection of primary side transformer, and oil-filled fuse switch combination unit, BS2692-1, IEC 60282-1, ESI 12-8, Breaking Capacity 40 kA
Delivery program

Product rangeFuseBasic functionOil fuse-linkField of applicationmedium voltageRated current [I]_N71 ARated voltageAC 15.5 kVConstruction sizeBS2692 F02Size63.5 x 359 mmUtilization categoryback-upStatus indicatorwith strikerDescriptionoil-tightBreaking Capacity40 kAusable for size/applicationsprotection of primary side transformer, and oil-filled fuse switch combination unitStandard/ApprovalBS IEC

ESIShapecylindricalStandards/RegulationsBS2692-1

IEC 60282-1

ESI 12-8Technical data ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507)Rated current71 ARated voltage15.5 kVVoltage typeACRated frequency50 - 50 HzBreaking capacity40 kAUtilization categoryOtherApplicationPrimary side transformer protectionLength359 mmDiameter63.5 mmPerformance category according to IEC 60282-1Back-upWith strikerYesStandardBritish StandardRelease characteristicOtherInstallation techniqueOil

ETIM for 15.5OHGMA71 Circuit breakers and fuses (EC003507)

Feature Name

Feature Value

Rated current (EF000227)

71 A

Rated voltage (EF000228)

15.5 kV

Voltage type....

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / 15.5KV 71AMP 2.5" OIL FUSE with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.