

INDUSTRIAL COMPONENT DATA

180AMP 240V AC BS88 FUSE 180LET EATON ELECTRIC

Fuse-link, high speed, 12 A, AC 240 V, BS88, 18 x 56 mm, aR,

..

Brand: EATON - MOELLER | Manufacturer Part Number: 180AMP 240V AC BS88 FUSE



Manufacturer	EATON - MOELLER
MPN / Reference	180AMP 240V AC BS88 FUSE
Catalog number	180LET
Category	HRC fuse
Minimum order	10 Pcs
Document ID	EO-C32D1DA041
Generated	2026-08-06

Product Overview

Fuse-link, high speed, 12 A, AC 240 V, BS88, 18 x 56 mm, aR, BS
180AMP 240V AC BS88 FUSE

Eaton Bussmann series high speed British standard fuse, 180A, 250 VAC/150 VDC (UL), Class aR, 200 kA RMS Sym.

Fuse, Fuse-link, high speed, 180 A, AC 240 V, DC 150 V, BS88, 18 x 56 mm, aR, BS, offset bolted tags, protection of DC common bus, DC drives, power converters/rectifiers and reduced voltage starters, BS88-4, IEC 60269-4, Breaking Capacity 200 kA, Optional accessories fuse-holder BH-0111

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path EATON - MOELLER > Bussmann Series High speed fuses

Additional Product Information

General specifications

Product Name Eaton Bussmann series high speed british standard fuse Catalog Number 180LET EAN 5027590466134

UPC 051712832083 Product Length/Depth 55 mm Product Height 18 mm Product Width 18 mm Product Weight 32 g

Compliances CE Marked

RoHS Compliant Certifications IEC Rated

UL Recognized

Designed and tested to BS88 part 4

UL recognized

IEC 60269-4 Electrical data

Amperage Rating 180 A Voltage rating 250 V Rated voltage AC 250 V Rated voltage DC 150 V Interrupt rating 200 kA RMS Sym, 50 kA DC at 150 Vdc Class Class aR Pre arc (I₂T) 1600 Clearing (I₂T) 29000 Watt losses 21 W Product specifications

Application Semiconductor, DC Common bus, DC drives, power converters/rectifiers Fuse indicator None Compatble Trip indicator/Microswitch

Suitable for EC-250 Trip indicator kit (indicator + clips)

TI250 Fuse indicator

MAI Microswitch/adaptor

MBI Microswitch/adaptor

ETIM for 180LET Circuit breakers and fuses (EC004556)

Feature Name

Feature Value

Fuse system according to IEC 60269 (EF017676)

Other

Fuse construction type according to IEC 60269 (EF015865)

Other

Type of current (EF000143)

AC

Rated voltage AC (EF007682)

250 V

Rated voltage DC (EF012281)

150 V

Rated current (EF000227)

180 A

Utilization category according to IEC 60269 (EF002572)

aR (accompanied semiconductor protection)

Breaking capacity (EF005617)

200 kA

Colour code (EF000931)

None

Type of fuse status indicator (EF004473)

None

Power loss at rated current (EF012389)

21 W

Mounting holes (EF021553)

M6

Ce...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / 180AMP 240V AC BS88 FUSE with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.