

INDUSTRIAL COMPONENT DATA

3.6KV 40AMP MOTORSTART 1.5" FUSE 3.6WJON640

3-6WJON640 EATON ELECTRIC Motor fuse-link, medium voltage, 40 A,..

Brand: EATON - MOELLER | Manufacturer Part Number: 3.6KV 40AMP MOTORSTART 1.5" FUSE



Manufacturer	EATON - MOELLER
MPN / Reference	3.6KV 40AMP MOTORSTART 1.5" FUSE
Catalog number	3-6WJON640
Category	Medium-/high voltage fuse
Minimum order	5 Pcs
Document ID	EO-4BD9EA4BB1
Generated	2026-08-06

Product Overview

3.6KV 40AMP MOTORSTART 1.5" FUSE

3.6KV 40AMP MOTORSTART 1.5" FUSE - Motor fuse-link, medium voltage, 40 A, AC 3.6 kV, 50 kA, 35 x 192 mm, back-up, BS

Fuse, Motor fuse-link, medium voltage, 40 A, AC 3.6 kV, 35 x 192 mm, back-up, BS, cylindrical, offset-bolts tags, motor protection, BS 2692-1, IEC 60282-1, Breaking Capacity 50 kA, Optional accessories, Supplied with

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	EATON - MOELLER > Bussmann Series Medium Voltage fuses and accessories
--------------	--

Additional Product Information

Motor fuse-link, medium voltage, 40 A, AC 3.6 kV, 50 kA, 35 x 192 mm, back-up, BS Fuse, Motor fuse-link, medium voltage, 40 A, AC 3.6 kV, 35 x 192 mm, back-up, BS, cylindrical, offset-bolts tags, motor protection, BS 2692-1, IEC 60282-1, Breaking Capacity 50 kA Delivery program

Product range Fuse Basic function Motor fuse-link Field of application medium voltage Rated current [I] 40 A Rated voltage AC 3.6 kV Size 35 x 192 mm Utilization category back-up Breaking Capacity 50 kA Suitable for size/applications motor protection Standard/Approval BS Shape cylindrical, offset-bolts tags Standards/Regulations BS 2692-1

IEC 60282-1 Technical data ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507) Rated current 40 A Rated voltage 3.6 kV Voltage type AC Rated frequency 50 - 50 Hz Breaking capacity 50 kA Utilization category Other Application Motor

protectionLength192 mmDiameter38.1 mmPerformance category according to IEC 60282-1Back-upWith
strikerNoStandardBritish StandardRelease characteristicOtherInstallation techniqueAir

ETIM for 3.6WJON640 Circuit breakers and fuses (EC003507)

Feature Name

Feature Value

Rated current (EF000227)

40 A

Rated voltage (EF000228)

3.6 kV

Voltage type (EF000187)

AC

Rated frequency (EF001663)

50 Hz

Breaking capacity (EF005617)

0.05 kA

Utilization category according to IEC 60269 (EF002572)

Other

Application (EF000041)

Motor protection

Length (EF001438)

257 mm

Diameter (EF000551)

35 mm

Performance category according to IEC 60282-1 (EF012539)

Back-up

With striker....

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / 3.6KV 40AMP MOTORSTART 1.5" FUSE with the required quantity to info@electricaonline.com
or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.