

INDUSTRIAL COMPONENT DATA

7.2KV 31.5A 3" MOTOR START FUSE 7.2WFNHO31.5 7-2WFNHO31-5 EATON ELECTRIC Motor fuse-link, medium voltage, 31..

Brand: EATON - MOELLER | Manufacturer Part Number: 7.2KV 31.5A 3" MOTOR START FUSE



Manufacturer	EATON - MOELLER
MPN / Reference	7.2KV 31.5A 3" MOTOR START FUSE
Catalog number	7-2WFNHO31-5
Category	Medium-/high voltage fuse
Minimum order	3 Pcs
Document ID	EO-BBDC2E92B9
Generated	2026-08-06

Product Overview

Motor fuse-link, medium voltage, 31.5 A, AC 7.2 kV, 76 x 403 mm, back-up, BS, with striker

7.2KV 31.5A 3" MOTOR START FUSE

7.2KV 31.5A 3" MOTOR START FUSE - Motor fuse-link, medium voltage, 31.5 A, AC 7.2 kV, 40 kA, 76 x 403 mm, back-up, BS, with striker

Fuse, Motor fuse-link, medium voltage, 31.5 A, AC 7.2 kV, 76 x 403 mm, back-up, BS, with striker, cylindrical, offset bolted tags, motor protection, BS2692-1, IEC 60282-1, Breaking Capacity 40 kA

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path

EATON - MOELLER > Busmann Series Medium Voltage fuses and accessories

Additional Product Information

General specifications

Product Name Eaton Busmann series medium voltage motor fuse Catalog Number 7.2WFNHO31.5 Model Code 7.2KV 31.5A 3" MOTOR START FUSE EAN 5027590488686 Product Length/Depth 403 mm Product Height 76 mm Product Width 76 mm Product Weight 4400 g Compliances CE Product specifications

Used with A3354730 Nickel-plated copper fuse clip Type fuse Application Motor protection Amperage Rating 31.5 A Fuse size 76 x 403 mm Breaking capacity 40 A Installation technique Air Performance Cat According To IEC 60282-1 Back-up Product application Motor protection Rated frequency - max 50 Hz Rated frequency - min 50 Hz Release characteristic Other Standard British Standard Utilization category Other Voltage type AC With striker Yes Class Class back-up Fuse

shape Cylindrical, offset bolted tags Watt losses 35 W Resistance 25.5 ohms Fuse diameter 76 mm Interrupt rating 40 kAIC
Construction size 76 x 403 mm Packaging type Standard Voltage rating 7.2 kV Fuse type WFNH
ETIM for 7.2WFNHO31.5 Circuit breakers and fuses (EC003507)

Feature Name

Feature Value

Rated current (EF000227)

31.5 A

Rated voltage (EF000228)

7.2 kV

Voltage type (EF000187)

AC

Rated frequency (EF001663)

50 Hz

Breaking capacity (EF005617)

0.04 kA

Utilization category according to IEC 60269 (EF002572)

Other

Application (EF000041)

Motor protection

Length (EF001438)

403 mm

Diameter (EF000551)

76 mm

Performance category according to IEC 60282-1 (EF012539)

Back-up

With striker (EF008175)

Yes

Standard (EF009322)

Britis...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / 7.2KV 31.5A 3" MOTOR START FUSE with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.