

INDUSTRIAL COMPONENT DATA

FAZ-B3,5/3N 278940 Y7-278940 EATON ELECTRIC Small circuit breaker

Brand: EATON - MOELLER | Manufacturer Part Number: FAZ-B3,5/3N



Manufacturer	EATON - MOELLER
MPN / Reference	FAZ-B3,5/3N
Catalog number	Y7-278940
Category	Miniature circuit breaker (MCB)
Minimum order	1 Pcs
Document ID	EO-8ADA398668
Generated	2026-08-05

Product Overview

Small circuit breaker

Miniature circuit breaker (MCB), 3.5 A, 3p+N, characteristic: B

Eaton Moeller series xEffect - FAZ MCB. FAZ, 3-pole+N, tripping characteristic: B, rated current I_n : 3.5 A, rated switching capacity (IEC/EN 60947-2): 15 kA

Miniature circuit breaker (MCB), FAZ, 3-pole+N, tripping characteristic: B, rated current I_n : 3.5 A, rated switching capacity (IEC/EN 60947-2): 15 kA, Switchgear for industrial and advanced commercial applications

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	EATON - MOELLER > Modular Switchgear - Industrial
--------------	---

Additional Product Information

General specifications

Product Name Eaton Moeller series xEffect - FAZ MCB Catalog Number 278940 Model Code FAZ-B3,5/3N EAN 4015082789404 Product Length/Depth 80 mm Product Height 75.5 mm Product Width 72 mm Product Weight 0.428 kg
Compliances RoHS conform Certifications EN45545-2

IEC 61373 Product specifications

Type Special features Ambient temperature hint: a 1 °C increase results in a 0.5% linear reduction of current carrying capacity Application Switchgear for industrial and advanced commercial applications

xEffect - Switchgear for industrial and advanced commercial applications

Amperage Rating 3.5 A Features Additional equipment possible

Concurrently switching N-neutral 10.10 Temperature rise The panel builder is responsible for the temperature rise

calculation. Eaton will provide heat dissipation data for the devices. 10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.13 Mechanical function The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. 10.2.2 Corrosion resistance Meets the product standard's requirements. 10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2.3.2 Verification of resistance of insulating materials to normal heat Meets the product standard's req...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / FAZ-B3,5/3N with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.