

INDUSTRIAL COMPONENT DATA

FUSE 1000A 1000V 3/110 AR 170L7299 EATON ELECTRIC

Fuse-link, high speed, 1000 A, AC 1000 V, Size 3, 76 x 90 ..

Brand: EATON - MOELLER | Manufacturer Part Number: FUSE 1000A 1000V 3/110 AR



Manufacturer	EATON - MOELLER
MPN / Reference	FUSE 1000A 1000V 3/110 AR
Catalog number	170L7299
Category	HRC fuse
Minimum order	1 Pcs
Document ID	EO-8A52595503
Generated	2026-08-06

Product Overview

Fuse-link, high speed, 1000 A, AC 1000 V, Size 3, 76 x 90 x 141 mm, aR, DIN, IEC, visual indicator, 110 mm centres
FUSE 1000A 1000V 3/110 AR

Fuse, Fuse-link, high speed, 1000 A, AC 1000 V, size 3, 76 x 90 x 141 mm, aR, DIN, IEC, visual indicator, square body with centre-bolted tags (slotted), semiconductor protection, DIN 43653, IEC 60269-4

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	EATON - MOELLER > Bussmann Series High speed fuses
--------------	--

Additional Product Information

General specifications

Product Name Eaton Bussmann series high speed square body fuse Catalog Number 170L7299 EAN 5996516008324
UPC 051712802543 Product Length/Depth 168 mm Product Height 76 mm Product Width 95 mm Product Weight 1262 g

Compliances CE

RoHS Compliant

EAC Certifications IEC 60269-4 Electrical data

Amperage Rating 1000 A Voltage rating 1000 V Voltage type AC Watt losses 155 W Breaking capacity 100 kA Class Class
aR Product specification

Fuse size 3

ETIM for 170L7299 Circuit breakers and fuses (EC004556)

Feature Name

Feature Value

Fuse system according to IEC 60269 (EF017676)
Other
Fuse construction type according to IEC 60269 (EF015865)
3
Type of current (EF000143)
AC
Rated voltage AC (EF007682)
1000 V
Rated current (EF000227)
1000 A
Utilization category according to IEC 60269 (EF002572)
aR (accompanied semiconductor protection)
Breaking capacity (EF005617)
100 kA
Colour code (EF000931)
None
Type of fuse status indicator (EF004473)
Top fuse status indicator
Power loss at rated current (EF012389)
155 W
Mounting holes (EF021553)
M10
Centre-to-centre distance of connections (EF021151)
108 mm

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / FUSE 1000A 1000V 3/110 AR with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.