

INDUSTRIAL COMPONENT DATA

FUSE 800A 1000V 3STN/140 AR 170L9588 EATON ELECTRIC

Fuse-link, high speed, 800 A, AC 1000 V, Size 3, 76 x 92..

Brand: EATON - MOELLER | Manufacturer Part Number: FUSE 800A 1000V 3STN/140 AR



Manufacturer	EATON - MOELLER
MPN / Reference	FUSE 800A 1000V 3STN/140 AR
Catalog number	170L9588
Category	HRC fuse
Minimum order	1 Pcs
Document ID	EO-C6A1A872D0
Generated	2026-08-06

Product Overview

Fuse-link, high speed, 800 A, AC 1000 V, Size 3, 76 x 92 x 171 mm, aR, IEC, single indicator

FUSE 800A 1000V 3STN/140 AR

Fuse, Fuse-link, high speed, 800 A, AC 1000 V, size 3, 76 x 92 x 171 mm, aR, IEC, single indicator, square body with centre-bolted tags (slotted), indicator style T for microswitch, Special type, semiconductor protection, IEC 60269-4

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path EATON - MOELLER > Bussmann Series High speed fuses

Additional Product Information

General specifications

Product Name Eaton Bussmann series high speed square body fuse Catalog Number 170L9588 EAN 5996516009017

Product Length/Depth 166 mm Product Height 75 mm Product Width 94 mm Product Weight 2300 g Compliances CE

RoHS Compliant

EAC Certifications IEC 60269-4 Electrical data

Amperage Rating 800 A Voltage rating 1000 V Voltage type AC Watt losses 135 W Breaking capacity 100 kA Class Class

aR Product specification

Fuse size 3

ETIM for 170L9588 Circuit breakers and fuses (EC004556)

Feature Name

Feature Value

Fuse system according to IEC 60269 (EF017676)

Other

Fuse construction type according to IEC 60269 (EF015865)

3

Type of current (EF000143)

AC

Rated voltage AC (EF007682)

1000 V

Rated current (EF000227)

800 A

Utilization category according to IEC 60269 (EF002572)

aR (accompanied semiconductor protection)

Breaking capacity (EF005617)

100 kA

Colour code (EF000931)

None

Type of fuse status indicator (EF004473)

Top fuse status indicator

Power loss at rated current (EF012389)

135 W

Mounting holes (EF021553)

Other

Centre-to-centre distance of connections (EF021151)

138 mm

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / FUSE 800A 1000V 3STN/140 AR with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.