


INDUSTRIAL COMPONENT DATA

Z-MG/WAK50 101620 Y7-101620 EATON ELECTRIC Measuring transformer, 50/5A 3 K., 1.5VA

Brand: EATON - MOELLER | Manufacturer Part Number: Z-MG/WAK50



Manufacturer	EATON - MOELLER
MPN / Reference	Z-MG/WAK50
Catalog number	Y7-101620
Category	Current transformer
Minimum order	1 Pcs
Document ID	EO-BDF3F10BD3
Generated	2026-08-06

Product Overview

Measuring transformer, 50/5A 3 K., 1.5VA

Z-MG/WAK50

Eaton Distribution parts. Measuring transformer, 50/5A 3 K., 1.5VA

Cable measuring transformer, primary rated operational current 50A, secondary rated current 5A, accuracy class 3, max. operational voltage 720V, rated frequency 50-60Hz, aperture diameter 22mm, mounting: quick attachment for top-hat rail IEC/EN 60715, wall mounting, directly to the cable, connection secondary plug-in terminals 6.3 mm

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	EATON - MOELLER > Modular Switchgear - Others and Accessories
--------------	---

Additional Product Information

General specifications

Product Name Eaton Distribution parts Catalog Number 101620 Model Code Z-MG/WAK50 EAN 4015081015122 Product Length/Depth 52 mm Product Height 56 mm Product Width 27 mm Product Weight 0.15 kg Compliances RoHS conform Product specifications

Opening width - min 0 mm Opening height - min 0 mm Nominal current 50 A Number of inputs (primary) 1 Opening diameter 22 mm Opening height - max 0 mm Secondary current input 5 A Secondary rated apparent power 0 VA Opening width - max 0 mm Accuracy class (ratio) 3 Model Through-feed current converter Mounting method Snap mounting Over current limiting factor FS 5 Secondary connection Plug-in connection

ETIM for 101620 Low-voltage industrial controls and switchgear (EC002048)

Feature Name

Feature Value

Model (EF000010)

Through-feed current converter

Rated primary current (EF007405)

50 A

Rated secondary current (EF007471)

5 A

Rated secondary apparent power (EF007470)

0 VA

Accuracy class (EF008842)

3

Overcurrent limiting factor (EF007511)

FS 5

Calibrated (EF008836)

No

With contact protection (EF008186)

No

Height opening (EF012757)

0 mm

Width opening (EF012758)

0 mm

Opening diameter (EF005153)

22 mm

Snap mounting (EF007462)

Yes

With copper rail (EF007380)

No

Secondary connection (EF021093)

Plug-in connection

Number of primary inputs (EF006947)

1

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / Z-MG/WAK50 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.