

INDUSTRIAL COMPONENT DATA

3.6KV 80Amp 2" MOTORSTART FUSE 3.6WDFHL80 3-6WDFHL80 EATON ELECTRIC Motor fuse-link, medium voltage, 63 A, A..

Brand: EATON - MOELLER | Manufacturer Part Number: 3.6KV 80Amp 2" MOTORSTART FUSE



Manufacturer	EATON - MOELLER
MPN / Reference	3.6KV 80Amp 2" MOTORSTART FUSE
Catalog number	3-6WDFHL80
Category	Medium-/high voltage fuse
Minimum order	3 Pcs
Document ID	EO-832BC1155F
Generated	2026-08-04

Product Overview

Motor fuse-link, medium voltage, 63 A, AC 3.6 kV, 51 x 254 mm, back-up, BS, with striker, no tags

3.6KV 80Amp 2" MOTORSTART FUSE

3.6KV 80Amp 2" MOTORSTART FUSE - Motor fuse-link, medium voltage, 80 A, AC 3.6 kV, 50 kA, 51 x 254 mm, back-up, BS, with striker

Fuse, Motor fuse-link, medium voltage, 80 A, AC 3.6 kV, 51 x 254 mm, back-up, BS, with striker, cylindrical, offset bolted tags, motor protection, BS2692-1, IEC 60282-1, Breaking Capacity 50 kA

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	EATON - MOELLER > Busmann Series Medium Voltage fuses and accessories
--------------	---

Additional Product Information

Motor fuse-link, medium voltage, 80 A, AC 3.6 kV, 50 kA, 51 x 254 mm, back-up, BS, with strikerFuse, Motor fuse-link, medium voltage, 80 A, AC 3.6 kV, 51 x 254 mm, back-up, BS, with striker, cylindrical, offset bolted tags, motor protection, BS2692-1, IEC 60282-1, Breaking Capacity 50 kADelivery program

Product rangeFuseBasic functionMotor fuse-linkField of applicationmedium voltageRated current [I]80 ARated voltageAC 3.6 kVSize51 x 254 mmUtilization categoryback-upStatus indicatorwith strikerBreaking Capacity50 kAusable for

size/applicationsmotor protectionStandard/ApprovalBSShapecylindrical

offset bolted tagsStandards/RegulationsBS2692-1

IEC 60282-1Technical data ETIM 7.0

Circuit breakers and fuses (EG000020) / Medium-/high voltage fuse (EC003507) Rated current 80 A Rated voltage 3.6 kV Voltage type AC Rated frequency 50 - 50 Hz Breaking capacity 50 kA Utilization category Other Application Motor protection Length 254 mm Diameter 51 mm Performance category according to IEC 60282-1 Back-up With striker Yes Standard British Standard Release characteristic Other Installation technique Air ETIM for 3.6WDFHL80 Circuit breakers and fuses (EC003507)

Feature Name

Feature Value

Rated current (EF000227)

80 A

Rated voltage (EF000228)

3.6 kV

Voltage type (EF000187)

AC

Rated frequency (EF001663)

50 Hz

Breaking capacity (EF005617)

0.05 kA

Utilization category according to IEC 60269 (EF002572)

Other

Application (EF000041)

Motor protection

Length (EF001438)

254 mm

Diameter (EF000551)

51 mm

Performance category accor...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / 3.6KV 80Amp 2" MOTORSTART FUSE with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.