

INDUSTRIAL COMPONENT DATA

FAZ-Z1/2 278817 Y7-278817 EATON ELECTRIC Over current switch, 1A, 2p, Z-Char, AC

Brand: EATON - MOELLER | Manufacturer Part Number: FAZ-Z1/2



Manufacturer	EATON - MOELLER
MPN / Reference	FAZ-Z1/2
Catalog number	Y7-278817
Category	Miniature circuit breaker (MCB)
Minimum order	1 Pcs
Document ID	EO-8F1E7132A9
Generated	2026-08-05

Product Overview

Over current switch, 1A, 2p, Z-Char, AC

FAZ-Z1/2

Eaton Moeller series xEffect - FAZ MCB. Miniature circuit breaker (MCB), 1 A, 2p, characteristic: Z

Miniature circuit breaker (MCB), FAZ, 2-pole, tripping characteristic: Z, rated current In: 1 A, Switchgear for industrial and advanced commercial applications

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	EATON - MOELLER > Modular Switchgear - Industrial
--------------	---

Additional Product Information

General specifications

Product Name Eaton Moeller series xEffect - FAZ MCB Catalog Number 278817 Model Code FAZ-Z1/2 EAN

4015082788179 Product Length/Depth 80 mm Product Height 75.5 mm Product Width 36 mm Product Weight 0.223 kg

Compliances UL CSA09 (with supplementary protector only)

RoHS conform Certifications UL (File No. E177451)

CE marking

CSA-C22.2 No. 235

UL (Category Control Number QVNU2, QVNU8)

IEC/EN 60947-2

UL 1077

CSA (Class No. 3215-30)

North America (UL recognized, CSA certified)

IEC/EN 60898

CSA (File No. 204453)

EN45545-2

IEC 61373 Product specifications

Type Special features Ambient temperature hint: a 1 °C increase results in a 0.5% linear reduction of current carrying capacity Application Branch circuits, not as BCPD

Switchgear for industrial and advanced commercial applications

xEffect - Switchgear for industrial and advanced commercial applications

Amperage Rating 1 A Voltage rating 240 V AC / 415 V AC Features Additional equipment possible 10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed. 10.12

Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function The device meets the requirements, provided the information in the instruction leaflet (IL)....

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send EATON - MOELLER / FAZ-Z1/2 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.