

INDUSTRIAL COMPONENT DATA

BFK1810A048 LOVATO CONTACTOR FOR POWER FACTOR CORRECTION WITH AC CONTROL CIRCUIT, BFK TYPE (INCLUDING LIMITI..

Brand: LOVATO ELECTRIC | Manufacturer Part Number: BFK1810A048



Manufacturer	LOVATO ELECTRIC
MPN / Reference	BFK1810A048
Catalog number	10000
Category	Capacitor contactor
Minimum order	1 Pcs
Document ID	EO-F2550A2661
Generated	2026-08-06

Product Overview

CONTACTOR FOR POWER FACTOR CORRECTION WITH AC CONTROL CIRCUIT, BFK TYPE (INCLUDING LIMITING RESISTORS), MAXIMUM IEC OPERATIONAL POWER 400V = 15KVAR, 48VAC 50/60HZ

3P CONTACTOR 15KVAR 48V 50/60HZ

Contactor for power factor correction with AC control circuit, including limiting resistors, maximum IEC operational power 400V = 15kvar, coil 48VAC 50/60Hz

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path LOVATO ELECTRIC > Industrial Contactors and Accessories - LOVATO ELECTRIC

Additional Product Information

BFK1810A048

Contactor for power factor correction with AC control circuit, including limiting resistors, maximum IEC operational power 400V = 15kvar, coil 48VAC 50/60Hz

Technical specifications

Type of product:Contactors for power factor correction with AC control circuitNumber of poles:3Type of coil:AC coil 50/60HzRated coil voltage [V]:48IEC operational power 400V [kvar]:15Type of built-in auxiliary contacts:1NOType of mounting:Screw / DIN rail 35mmOrder code BFK1810A048

Weight [g] 460

Qty. per package 10

Multiple qty. of packs per order 10

Package dimensions [mm] 265X265X135

Volume [cm³] 948.038

Bar code [EAN13] 8013975163269

HS Code 85365080

87.53 £

ETIM for BFK1810A048 Low-voltage industrial controls and switchgear (EC001079)

Feature Name

Feature Value

Voltage type for actuating (EF008242)

AC

Type of electrical connection of main circuit (EF006819)

Screw connection

Rated control supply voltage AC 60 Hz (EF003979)

48 V

Rated control supply voltage AC 50 Hz (EF003978)

48 V

Rated reactive power at 400 V, 50 Hz (EF007044)

15 kvar

Number of auxiliary contacts as normally closed contact (EF001377)

0

Number of auxiliary contacts as normally open contact (EF001376)

0

Number of normally closed contacts as main contact (EF001375)

0

Number of normally open contacts as main contact (EF001374)

3

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send LOVATO ELECTRIC / BFK1810A048 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.