

INDUSTRIAL COMPONENT DATA

**BF38T4A400 LOVATO FOUR-POLE CONTACTOR, IEC
OPERATING CURRENT ITH (AC1) 56A, AC COIL 50/60HZ,
400VAC**

Brand: LOVATO ELECTRIC | Manufacturer Part Number: BF38T4A400



Manufacturer	LOVATO ELECTRIC
MPN / Reference	BF38T4A400
Catalog number	10000
Category	Power contactor, AC switching
Minimum order	1 Pcs
Document ID	EO-2955C880A2
Generated	2026-08-04

Product Overview

FOUR-POLE CONTACTOR, IEC OPERATING CURRENT ITH (AC1) = 56A, AC COIL 50/60HZ, 400VAC

4P CONTACTOR NO 56A AC1 400/50-60

Four-pole contactor, IEC operating current Ith (AC1) = 56A, AC coil 50/60Hz, 400VAC

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path LOVATO ELECTRIC > Industrial Contactors and Accessories - LOVATO ELECTRIC

Additional Product Information

BF38T4A400

Four-pole contactor, IEC operating current Ith (AC1) = 56A, AC coil 50/60Hz, 400VAC

Technical specifications

Type of product: Contactors Number of poles: 4 Type of coil: AC coil 50/60Hz Rated coil voltage [V]: 400 IEC operating current Ith (AC1) [A]: 56 IEC operating current and power Ie (AC3) 400V [A/Kw]: 38A / 18.5Kw UL/CSA horsepower ratings 480V [HP]: 30 Type of mounting: Screw / DIN rail 35mm Order code BF38T4A400

Weight [g] 518

Qty. per package 1

Multiple qty. of packs per order 1

Package dimensions [mm] 097X065X090

Volume [cm³] 567.45

Bar code [EAN13] 8013975161852
HS Code 85365080
170.91 £
ETIM for BF38T4A400 Low-voltage industrial controls and switchgear (EC000066)
Feature Name
Feature Value
Voltage type for actuating (EF008242)
AC
Type of electrical connection of main circuit (EF006819)
Screw connection
Rated control supply voltage AC 60 Hz (EF003979)
400 V
Rated control supply voltage AC 50 Hz (EF003978)
400 V
Modular version (EF001126)
No
Rated operation current I_e at AC-4, 400 V (EF008495)
15.5 A
Rated operation current I_e at AC-1, 400 V (EF001393)
56 A
Rated operation current I_e at AC-3, 400 V (EF001392)
38 A
Number of auxiliary contacts as normally closed contact (EF001377)
0
Number of auxiliary contacts as normally open contact (EF001376)
0
Number of normally closed contacts as main contact (EF001375)
0
Number of normally open contacts as main contact (EF001374)
4
Rated operation power at AC-3, 400 V (EF001364)
18.5 kW

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send LOVATO ELECTRIC / BF38T4A400 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.