

INDUSTRIAL COMPONENT DATA

BF80T2A110 LOVATO FOUR-POLE CONTACTOR, IEC OPERATING CURRENT ITH (AC1) 115A, AC COIL 50/60HZ, 110VAC, 2NO AN..

Brand: LOVATO ELECTRIC | Manufacturer Part Number: BF80T2A110



Manufacturer	LOVATO ELECTRIC
MPN / Reference	BF80T2A110
Catalog number	10000
Category	Power contactor, AC switching
Minimum order	1 Pcs
Document ID	EO-323127C66F
Generated	2026-08-05

Product Overview

FOUR-POLE CONTACTOR, IEC OPERATING CURRENT ITH (AC1) = 115A, AC COIL 50/60HZ, 110VAC, 2NO AND 2NC 2NO+2NC CONTACT. 115A AC1 110VAC 50/60HZ

Four-pole contactor, IEC operating current Ith (AC1) = 115A, AC coil 50/60Hz, 110VAC, 2NO and 2NC

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	LOVATO ELECTRIC > Industrial Contactors and Accessories - LOVATO ELECTRIC
--------------	---

Additional Product Information

BF80T2A110

Four-pole contactor, IEC operating current Ith (AC1) = 115A, AC coil 50/60Hz, 110VAC, 2NO and 2NC

Technical specifications

Type of product: Contactors Number of poles: 4 Type of coil: AC coil 50/60Hz Rated coil voltage [V]: 110 IEC operating current Ith (AC1) [A]: 115 IEC operating current and power Ie (AC3) 400V [A/Kw]: 80A / 45Kw UL/CSA horsepower ratings 480V [HP]: 60 Type of mounting: Screw / DIN rail 35mm Order code BF80T2A110

Weight [g] 1360

Qty. per package 1

Multiple qty. of packs per order 1

Package dimensions [mm] 127X102X146

Volume [cm³] 1891

Bar code [EAN13] 8013975224120

HS Code 85365080

716.83 £

ETIM for BF80T2A110 Low-voltage industrial controls and switchgear (EC000066)

Feature Name

Feature Value

Voltage type for actuating (EF008242)

AC

Type of electrical connection of main circuit (EF006819)

Frame clamp

Rated control supply voltage AC 60 Hz (EF003979)

110 V

Rated control supply voltage AC 50 Hz (EF003978)

110 V

Modular version (EF001126)

No

Rated operation current I_e at AC-1, 400 V (EF001393)

115 A

Rated operation current I_e at AC-3, 400 V (EF001392)

80 A

Number of auxiliary contacts as normally closed contact (EF001377)

0

Number of auxiliary contacts as normally open contact (EF001376)

0

Number of normally closed contacts as main contact (EF001375)

2

Number of normally open contacts as main contact (EF001374)

2

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send LOVATO ELECTRIC / BF80T2A110 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.