

INDUSTRIAL COMPONENT DATA

BFK1210A04860 LOVATO CONTACTOR FOR POWER FACTOR CORRECTION WITH AC CONTROL CIRCUIT, BFK TYPE (INCLUDING LIMII..

Brand: LOVATO ELECTRIC | Manufacturer Part Number: BFK1210A04860



Manufacturer	LOVATO ELECTRIC
MPN / Reference	BFK1210A04860
Catalog number	04860
Category	Capacitor contactor
Minimum order	10 Pcs
Document ID	EO-CFE95A5173
Generated	2026-07-29

Product Overview

CONTACTOR FOR POWER FACTOR CORRECTION WITH AC CONTROL CIRCUIT, BFK TYPE (INCLUDING LIMITING RESISTORS), MAXIMUM IEC OPERATIONAL POWER 400V = 12.5KVAR, 48VAC 60HZ

3P CONTACTOR 12,5KVAR 48V 60HZ

Contactor for power factor correction with AC control circuit, including limiting resistors, maximum IEC operational power 400V = 12.5kvar, coil 48VAC 60Hz

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	LOVATO ELECTRIC > Industrial Contactors and Accessories - LOVATO ELECTRIC
--------------	---

Additional Product Information

BFK1210A04860

Contactor for power factor correction with AC control circuit, including limiting resistors, maximum IEC operational power 400V = 12.5kvar, coil 48VAC 60Hz

Technical specifications

Type of product:Contactors for power factor correction with AC control circuitNumber of poles:3Type of coil:AC coil 60HzRated coil voltage [V]:48IEC operational power 400V [kvar]:12.5Type of built-in auxiliary contacts:1NOType of mounting:Screw / DIN rail 35mmOrder code BFK1210A04860

Weight [g] 416

Qty. per package 10

Multiple qty. of packs per order 10
Package dimensions [mm] 265X265X135
Volume [cm³] 948.038
Bar code [EAN13] 8013975163191
HS Code 85365080
93.88 £
ETIM for BFK1210A04860 Low-voltage industrial controls and switchgear (EC001079)
Feature Name
Feature Value
Voltage type for actuating (EF008242)
AC
Type of electrical connection of main circuit (EF006819)
Screw connection
Rated control supply voltage AC 60 Hz (EF003979)
48 V
Rated reactive power at 400 V, 50 Hz (EF007044)
12.5 kvar
Number of auxiliary contacts as normally closed contact (EF001377)
0
Number of auxiliary contacts as normally open contact (EF001376)
0
Number of normally closed contacts as main contact (EF001375)
0
Number of normally open contacts as main contact (EF001374)
3

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send LOVATO ELECTRIC / BFK1210A04860 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.