

INDUSTRIAL COMPONENT DATA

86060 MURRELEKTRONIK MET 1-PHASE CONTROL AND ISOLATION TRANSFORMER P: 1500VA IN: 230VAC+/- 5% OUT: 230VAC

Brand: MURRELEKTRONIK | Manufacturer Part Number: 86060



Manufacturer	MURRELEKTRONIK
MPN / Reference	86060
Catalog number	86060
Category	Transformers
Minimum order	1 unit
Document ID	EO-2CF0FDF562
Generated	2026-08-06

Product Overview

86060 MURRELEKTRONIK MET 1-PHASE CONTROL AND ISOLATION TRANSFORMER P: 1500VA IN: 230VAC+/- 5% OUT: 230VAC

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	MURRELEKTRONIK > Transformers
--------------	-------------------------------

Additional Product Information

Single-phase - Control and Isolation Transformers

1500 VA

Isolation class T 60/B

General dataStandards EN 61558-1, EN 61558-2-4, EN 62041 category 0

Test isolation voltage 4 kV (prim./sec.)

Dimensions H×W×D 168×174×162 mm

Fixing centers a×b×c 141.5×135×7 mm

Drill hole Ø 7×11 mm

Mounting method Key-hole mounting

Temperature range -20...+60 °C (storage temperature -40...+80 °C)

OutputOutput voltage 230 V AC

Output rating 1500 VA

Input voltage 230 V AC $\pm 5\%$
Frequency 50...60 Hz
Input current 6.9 A (230 V AC)
Short-circuit current 358.1 A (230 V AC)
Inrush current 85.07 A (230 V AC)
Commercial data country of origin CZ
customs tariff number 85043200
EAN 4048879078856
eClass 27031302
Packaging unit 1

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send MURRELEKTRONIK / 86060 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.