

**INDUSTRIAL COMPONENT DATA**

# 6120028 OBO BETTERMANN POWER OUTLET STD-D0 ROJO2

Brand: OBO BETTERMANN | Manufacturer Part Number: STD-D0 SRO2



|                 |                |
|-----------------|----------------|
| Manufacturer    | OBO BETTERMANN |
| MPN / Reference | STD-D0 SRO2    |
| Catalog number  | 6120028        |
| Category        | Socket outlet  |
| Minimum order   | 1 Pcs          |
| Document ID     | EO-DF9156FFE6  |
| Generated       | 2026-08-01     |

## Product Overview

**POWER OUTLET STD-D0 ROJO2**

0° socket, protective contact, double. Power socket, double 0°, with increased touch protection with screwless terminals, 2-pin, 16 A, 250 V~, with connection terminals to IEC 60884-1. For installation in Rapid 45 trunking, device installation trunking, service poles, underfloor systems and desk boxes.

**STRUCTURED PRODUCT DATA**

## Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

## Classification & Catalog Path

Catalog path      OBO BETTERMANN &gt; EGS device systems - OBO BETTERMANN

## Additional Product Information

Approvals VDE  
 Closable no  
 CO2 Footprint (GWP) Cradle-to-Gate 0,308 kg CO2e / 1 Piece  
 Coding no  
 Colour Signal red; RAL 3001  
 Connection type Screwless terminal  
 Cover Central plate  
 Depth 42 mm  
 Dimension 250V, 10/16A  
 Ejection mechanism no  
 Error current protection no  
 Fastening type Lock  
 For more difficult conditions (according to VDE) no

Halogen-free yes  
Height 45 mm  
Hinged cover no  
increased touch protection yes  
Insulated installation no  
Labelling panel no  
Material Polycarbonate  
Mounting type Device installation duct  
Nominal current 16 A  
Nominal voltage 250 V  
Number of poles 2  
Number of units 2  
Operating temperature, max. 40 °C  
Operating temperature, min. -5 °C  
Power reserve no  
Printed label/coding Without printing  
Protection rating Other  
Rotated central insert no  
Socket angle 0°  
Socket version Protective contact  
Special power supply Without special power supply  
Surface version Matt  
Surge protection no  
Transparent no  
Version for Double 0°  
Warning light no  
Width 90 mm  
With fine-wire fuse no  
With functional lighting no  
With on/off switch no  
With orientation lighting no

## REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send OBO BETTERMANN / STD-D0 SRO2 with the required quantity to [info@electricaonline.com](mailto:info@electricaonline.com) or use [electricaonline.com/request-quote](https://electricaonline.com/request-quote).

### GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.