


INDUSTRIAL COMPONENT DATA

254 DIN 8-10 CU 5314135 OBO BETTERMANN

Cross-connectors , 8-10mm, Copper, Cu

Brand: OBO BETTERMANN | Manufacturer Part Number: 254 DIN 8-10 CU



Manufacturer	OBO BETTERMANN
MPN / Reference	254 DIN 8-10 CU
Catalog number	5314135
Category	Connector for lightning protection
Minimum order	10 Pcs
Document ID	EO-8501112C66
Generated	2026-08-01

Product Overview

Cross-connectors , 8-10mm, Copper, Cu

Cross-connector with intermediate plate for Rd 8–10 mm Cu. • Meets the requirements of VDE 0185-305-3 (IEC/ EN 62305-3)• Fit: Rd 8-10 x Rd 8-10• With adapter plate• Mounted with 4 hexagonal bolts M6 x 20 and 4 hexagonal nuts M6 (F)made of rustproof steel (VA)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path OBO BETTERMANN > TBS Transient and lightning protection systems - OBO BETTERMANN > Surge , external

Additional Product Information

CO2 Footprint (GWP) Cradle-to-Gate 0,6454 kg CO2e / 1 Piece

Dimension 8-10mm

Dimension A 52 mm

Dimension B 52 mm

Fit Rd 8-10 mm

Intermediate plate yes

Lightning current carrying capacity H/100 kA

Material Copper

Suitable for connection Round conductor Rd 8-10 / Rd 8-10

Type of connector Cross-connectors

Type of fastening screw Hexagonal bolt

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send OBO BETTERMANN / 254 DIN 8-10 CU with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.