

INDUSTRIAL COMPONENT DATA

A1000-FIA3480-RE 328915 A1000FIA3480RE OMRON Filter input 400V three-phase 480A (A1000-L1000)

Brand: OMRON | Manufacturer Part Number: A1000-FIA3480-RE



Manufacturer	OMRON
MPN / Reference	A1000-FIA3480-RE
Catalog number	A1000FIA3480RE
Category	Accessories/spare parts for frequency controller
Minimum order	1 Pcs
Document ID	EO-EBA1CC6A0C
Generated	2026-07-31

Product Overview

Filter input 400V three-phase 480A (A1000-L1000)

Input filter 400V three-phase 480A (A1000-L1000)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path OMRON > Frequency inverters > Accessories

Additional Product Information

Current vector control, with or without PG

High starting torque (200% / 0.3 Hz, spd range 1:200 OLV), (200% at 0 r/min, spd range 1:1500 CLV)

Double rating ND 120%/1min and HD 150%/1 min

Advanced Auto-Tuning for IM & PM Motors

Open Loop Control of PM Motors

Low-noise Low carrier technology

10 years lifetime design

Screw-less terminals

Control Terminals with memory backup

24 VDC control board power supply option

Fieldbus communications: Modbus, Profibus, CANopen, DeviceNet, ML-II, PROFINET, EtherCAT and EtherNet/IP

Safety embedded: EN954-1 safety cat. 3, stop category 0, IEC EN 61508 SIL 2 and EN61800-5-1 with EDM

Regenerative solutions as option

CE, UL, cUL and TUV

Accessories**Regenerative accessories**

D1000 kit - DC Supply with Regenerative Active Front End system

Regenerative DC bus supply unit (D1000)

Reference: CIMR-DC_

4A0005

4A0010

4A0020

4A0030

4A0040

4A0060

4A0100

4A0130

4A0185

4A0270

4A0370

4A0630

Max. applicable motor capacity (kW)

3.7

7.5

15

22

30

45

75

110

160

220

315

560

Rated output capacity (kW)¹

5

10

20

30

40

60

100

130

185

270

370

630

Rated input current AC (A)

8

16

30

43

58

86

145

210

300

410

560

1040

Rated output current DC (A)

8

15

30

45

61

91

152

197

280

409

561

955

Rated input voltage

3-phase 380 to 480 VAC

Rated output voltage

660 VDC

Rated frequency

50/60 Hz

Input power factor

> 0.99

Carrier frequency

6

4

2

Degree of protection

IP20 (CIMR-DC4A0005 to CIMR-DC4A0020 models)

IP00 (CIMR-DC4A0030 to CIMR-DC4A0630 models)

Ambient humidity

95% RH or less (wit...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send OMRON / A1000-FIA3480-RE with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.