INDUSTRIAL COMPONENT DATA

FA MCR-EX-HT-1TS-I-OLP 1145217 PHOENIX CONTACT Ex i-Output loop-fed head transmitter for transmitting RTD an..

Brand: PHOENIX CONTACT | Manufacturer Part Number: FA MCR-EX-HT-1TS-I-OLP

PRODUCT IMAGE\nNOT AVAILABLE

Manufacturer	PHOENIX CONTACT
MPN / Reference	FA MCR-EX-HT-1TS-I-OLP
Catalog number	1145217
Category	Temperature transformer
Minimum order	1 Pcs
Document ID	EO-6E2D5B6038
Generated	2026-11-18

Product Overview

Ex i-Output loop-fed head transmitter for transmitting RTD and CT sensor signals as well as resistance and voltage transmitters using 4 mA... 20 mA. HART, Standard Configuration, Screw Connection
Output loop-fed head transmitter to transmit thermoresistance and TC sensor signals, as well as resistance and voltage transmitters via HART or 4 mA ... 20 mA, freely configurable, intrinsically safe, with screw connection.

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	PHOENIX CONTACT > INTERFACE Components (IF)

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / FA MCR-EX-HT-1TS-I-OLP with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES
Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.