INDUSTRIAL COMPONENT DATA

FRONT-FMC 1,5/D28-FF-6,35-R BD 1097918 PHOENIX CONTACT Connector for printed circuit board, number of poles:..

Brand: PHOENIX CONTACT | Manufacturer Part Number: FRONT-FMC 1,5/D28-FF-6,35-R BD

PRODUCT IMAGE\nNOT AVAILABLE

Manufacturer	PHOENIX CONTACT
MPN / Reference	FRONT-FMC 1,5/D28-FF-6,35-R BD
Catalog number	1097918
Category	Cable connector
Minimum order	1000 Pcs
Document ID	EO-FB1079F67D
Generated	2026-11-19

Product Overview

Connector for printed circuit board, number of poles: 28, step: 6.35 mm, type of connection: spring clamp push-in, color: light grey, surface contacts: Tin
Connector for printed circuit board, nominal section: 1.5 mm², color: light gray, rated current: 6 A, dimensioning voltage (III/2): 320 V, surface contacts: Tin, contact type: Connection female, Number of rows: 2, Number of poles per row: 28, article family: FRONT-FMC 1.5/.. -FF, pitch: 6.35 mm, connection type: Push-in spring connection, conductor/printed circuit board connection direction: 0°, pin arrangement: Linear pin arrangement, Lock: Screw lock, packaging type: boxed packaging

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	PHOENIX CONTACT > PCB Connectors (PCC)

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / FRONT-FMC 1,5/D28-FF-6,35-R BD with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.